

Programmable Linear Hall IC with Advanced Diagnostics for Safety-Critical Applications

FEATURES AND BENEFITS

- High-speed analog, A-to-D converter (ADC), and digital architectures, enabling user-selectable bandwidth for speed-sensitive applications
 - 4-phase chopper stabilization, which minimizes offset drift across temperature range
 - 16-bit, high update rate ADC
- Automotive AEC-Q100 qualified
- Exceptional stability throughout lifetime and across temperature changes
 - Factory-configured using multisegment temperature compensation to give a flat baseline across operating temperature range
 - Customer configurability for 1st and 2nd order sensitivity and 1st order offset compensation across temperature range
 - Integrated feedback coil compensates for drift throughout product lifetime

Continued on the next page...

PACKAGE:

3-pin SIP (suffix UC)



Not to scale

DESCRIPTION


The A1342 device is a high-precision, programmable Hall-effect linear sensor integrated circuit (IC) with an open-drain output, for both automotive and nonautomotive applications. The signal path of the A1342 provides flexibility through external programming that allows the generation of an accurate, and customized, output from an input magnetic signal.

The A1342 is an especially configurable and robust solution for the most demanding linear field sensor applications. The BiCMOS, monolithic IC incorporates a Hall sensing element, precision temperature-compensating circuitry to reduce the intrinsic sensitivity and offset drift of the Hall element, a small-signal high-gain amplifier, proprietary dynamic offset cancellation circuits, advanced output linearization circuitry, and advanced diagnostics. The A1342 provides an unmatched level of customer-programmable options.

A key feature of the A1342 is its ability to produce a highly linear device output for nonlinear input magnetic fields. To achieve this, the device features 16-segment customer-programmable linearization, where a unique linearization coefficient factor is applied to each segment. Linearization coefficients are stored in a look-up table in EEPROM.

The A1342 has two configurable output options: SENT or PWM. In addition to SAEJ2716, the A1342 includes two additional proprietary SENT options: SSENT and ASENT. Both protocols enable bus configurations with up to four devices on one SENT line to reduce system costs. SSENT provides sequential

Continued on the next page...



Functional Block Diagram

Description (continued)

access to the sensors connected to the same line. SSENT provides a very low overhead method to maximize the sensor bandwidth on this single SENT line, minimizing impact on system performance. ASENT provides random access to all the sensors on the common SENT line. Both protocols allow individual sensors on the same line to enter diagnostic mode while the other sensors continue to

respond to queries, allowing for the highest diagnostic coverage while maintaining 100% availability of the sensor solution.

The A1342 is available in a through-hole, lead (Pb) free 3-pin SIP package (UC suffix), with 100% matte-tin leadframe plating.

Features and Benefits (continued)

- Wide operating flexibility to meet any application:
 - Input field range up to ± 1500 G
 - Rail to negative rail offset configurability
 - High-precision, full output range high and low clamps
 - Integrated linearization allows for flexible output waveform translation and compensation for nonlinear magnetic inputs
 - Integrated capacitors offer extremely robust ESD performance and enhanced EMC performance
- Advanced diagnostic-focused features enabling easier system-level ASIL compliance
 - Full data path validation through active front-end stimulation with internal magnetic coil; this method validates all relevant transistors for device operation
 - Logic Built-In Self Test (LBIST) on-demand to validate the digital subsystem
 - Large suite of configurable fault monitors provide system level fault detection, including:
 - ◆ Overvoltage or undervoltage
 - ◆ Overtemperature
 - ◆ Magnetic Field Out of Range detection
 - ◆ Broken wire detection
- Flexible output protocols with up to 12-bit resolution and configurable error notifications
 - Digital open-drain output allows for flexible output voltage levels
 - PWM (Pulse-Width-Modulated) output with diagnostic output mode to identify fault conditions
 - SENT (Single Edge Nibble Transmission) compliant output with configurable reporting of error conditions and other diagnostic information
 - Proprietary Fast SENT provides increased data rates to support high-bandwidth applications
 - Device-shared SENT protocol as SSENT (Sequential SENT) and ASENT (Addressable SENT) allows user to connect up to four devices on the same output line for faster communication.
 - Enhanced EMC tuning through programmable fall-time configurability
- Integrated EEPROM enables a high level of configurability and product traceability
 - Customer-reserved area allows on-board storage of unique lot and date code information
 - Robust EEPROM with Single Error Correction and Double Error Detection (SECDED) capability
 - Integrated charge pump allows in-application programming without any requirement for high voltages to be supplied to the device during programming

SELECTION GUIDE

| Part Number | Packing [1] |
|--------------|-----------------------------|
| A1342LUCTN-T | 4000 pieces per 13-in. reel |

¹ Contact Allegro™ for additional packing options



Table of Contents

| | | | |
|----------------------------------|----|------------------------------------|----|
| Functional Block Diagram | 1 | Linear Output Protocols | 18 |
| Specifications | 4 | PWM Output Mode (outmsg_mode = 0) | 18 |
| Absolute Maximum Ratings | 4 | SENT Output Modes | 20 |
| Thermal Characteristics | 4 | Message Structure | 20 |
| Pinout Diagram and Terminal List | 4 | Optional Short Serial Message | 21 |
| Operating Characteristics | 5 | Data Nibble Format | 21 |
| Magnetic Characteristics | 7 | Checksum (CRC) Nibble | 22 |
| Accuracy Characteristics | 8 | Output Driver Fall Time Selection | 22 |
| Programmable Characteristics | 9 | SAEJ2716 SENT and TSENT | 24 |
| Application Information | 10 | SSENT Addressing Protocol | 27 |
| Signal Path | 11 | SSENT Function Pulses | 28 |
| Compensation Block | 11 | ASENT Addressing Protocol | 30 |
| Linearization | 12 | ASENT Function Pulses | 31 |
| Post-Linearization Trim | 14 | Serial Communication | 31 |
| Clamp | 14 | Programming Information | 32 |
| Diagnostic Conditions | 15 | Serial Interface Message Structure | 35 |
| Diagnostic Modes | 15 | Read and Write Transmission | 36 |
| Diagnostic Configuration | 15 | CRC | 36 |
| Analog Signal Path | 15 | Customer Factory Access | 37 |
| BIST | 16 | Customer Memory Lock | 37 |
| ADC Overflow | 17 | EEPROM Margin Checking | 37 |
| Undervoltage Detection and Reset | 17 | Memory Address Map | 38 |
| Broken Ground Detection | 17 | Programmable Parameter Reference | 43 |
| EEPROM Diagnostics | 17 | Package Outline Drawing | 47 |

SPECIFICATIONS

ABSOLUTE MAXIMUM RATINGS


| Characteristic | Symbol | Notes | Rating | Unit |
|-------------------------------|-------------------|--|------------|------|
| Forward Supply Voltage | V_{CC} | | 20 | V |
| Reverse Supply Voltage | V_{RCC} | | -16 | V |
| Forward Supply Current | I_{CC} | | 30 | mA |
| Reverse Supply Current | I_{RCC} | | -30 | mA |
| Forward Output Voltage | V_{OUT} | | 20 | V |
| Reverse Output Voltage | V_{ROUT} | | -1 | V |
| Output Short-Circuit Current | $I_{OUTSC(SINK)}$ | V_{CC} to V_{OUT} , $4.5\text{ V} < V_{CC} < 5.5\text{ V}$ | -20 | mA |
| Operating Ambient Temperature | T_A | L temperature range | -40 to 150 | °C |
| Maximum Junction Temperature | $T_J(\text{max})$ | | 165 | °C |
| Storage Temperature | T_{stg} | | -65 to 165 | °C |

THERMAL CHARACTERISTICS: May require derating at maximum conditions; see application information

| Characteristic | Symbol | Test Conditions [1] | Value | Unit |
|----------------------------|-----------------|--|-------|------|
| Package Thermal Resistance | $R_{\theta JA}$ | 1-layer PCB with copper limited to solder pads | 201 | °C/W |

[1] Additional thermal information available on the Allegro website.

PINOUT DIAGRAM AND TERMINAL LIST TABLE



Terminal List Table

| Number | Name | Function |
|--------|------|------------------------|
| 1 | VCC | Input power supply [2] |
| 2 | GND | Ground |
| 3 | VOUT | Output signal |

[2] Allegro offers LDOs well-suited for regulated sensor applications. For available devices, visit www.allegromicro.com/en/Products/Regulators-And-Lighting/Single-Output-Regulators, or contact your local Allegro sales representative.

Package UC, 3-Pin SIP Pinout Diagram

OPERATING CHARACTERISTICS: Valid T_A and V_{CC} , unless otherwise specified

| Characteristics | Symbol | Test Conditions | Min. | Typ. | Max. | Unit |
|-----------------------------------|-------------------|---|------|------|------|---------------|
| ELECTRICAL CHARACTERISTICS | | | | | | |
| Supply Voltage | V_{CC} | | 4.5 | 5 | 5.5 | V |
| Supply Current | I_{CC} | Compensation coil off | – | – | 10 | mA |
| Peak Supply Current | $I_{CC(pk)}$ | Compensation coil on | – | – | 16 | mA |
| Reverse Supply Current | I_{RCC} | $V_{CC} = -16\text{ V}$, $T_A = 25^\circ\text{C}$ | -3 | – | – | mA |
| Supply Zener Clamp Voltage | $V_{ZSUPPLY}$ | $I_{CC} = 13\text{ mA}$, compensation coil off, $T_A = 25^\circ\text{C}$ | 20 | – | – | V |
| Chopping Frequency | f_C | $T_A = 25^\circ\text{C}$, compensation coil off | – | 128 | – | kHz |
| | | $T_A = 25^\circ\text{C}$, compensation coil on | – | 64 | – | kHz |
| Oscillator Frequency | f_{OSC} | $T_A = 25^\circ\text{C}$ | 6963 | 8192 | 9421 | kHz |
| Undervoltage Detection Threshold | $V_{CC(UV)LOW}$ | V_{CC} falling, see Figure 1 | 4 | – | 4.35 | V |
| | $V_{CC(UV)HIGH}$ | V_{CC} rising, see Figure 1 | 4.05 | – | 4.4 | V |
| Power-On-Reset Threshold | $V_{CC(POR)LOW}$ | V_{CC} falling, see Figure 1 | 3.4 | – | 3.8 | V |
| | $V_{CC(POR)HIGH}$ | V_{CC} rising, see Figure 1 | 3.5 | – | 3.9 | V |
| Overvoltage Detection Threshold | $V_{CC(OV)LOW}$ | V_{CC} falling, see Figure 1 | 6.6 | – | 7.4 | V |
| | $V_{CC(OV)HIGH}$ | V_{CC} rising, see Figure 1 | 6.7 | – | 7.6 | V |
| High-Voltage Threshold | $V_{CC(HV)LOW}$ | V_{CC} falling, see Figure 1 | 15 | – | – | V |
| | $V_{CC(HV)HIGH}$ | V_{CC} rising, see Figure 1 | – | – | 17 | V |
| OUTPUT CHARACTERISTICS | | | | | | |
| Bandwidth [1] | BW | $bw_sel_c = 0$ | – | 40 | – | Hz |
| | | $bw_sel_c = 1$ | – | 160 | – | Hz |
| | | $bw_sel_c = 2$ | – | 680 | – | Hz |
| | | $bw_sel_c = 3$ | – | 3000 | – | Hz |
| | | $bw_sel_c = 4-7$ | – | 7400 | – | Hz |
| Noise (Peak-to-Peak) [2] | $OUT_{N(PK-PK)}$ | $bw_sel_c = 0$, $T_A = 25^\circ\text{C}$, $coil_freq = 0$, $coilcomp_dis = 0$, $bw_sel_comp_c = 0$ | – | 0.32 | – | G |
| | | $bw_sel_c = 1$, $T_A = 25^\circ\text{C}$, $coil_freq = 0$, $coilcomp_dis = 0$, $bw_sel_comp_c = 0$ | – | 0.50 | – | G |
| | | $bw_sel_c = 2$, $T_A = 25^\circ\text{C}$, $coil_freq = 0$, $coilcomp_dis = 0$, $bw_sel_comp_c = 0$ | – | 0.93 | – | G |
| | | $bw_sel_c = 3$, $T_A = 25^\circ\text{C}$, $coil_freq = 0$, $coilcomp_dis = 0$, $bw_sel_comp_c = 0$ | – | 1.74 | – | G |
| | | $bw_sel_c = 4$, $T_A = 25^\circ\text{C}$, $coil_freq = 0$, $coilcomp_dis = 0$, $bw_sel_comp_c = 0$ | – | 2.85 | – | G |
| Output Leakage Current | I_{OUT} | Output voltage $\leq 5.5\text{ V}$, output FET off | – | – | 100 | μA |
| Output Load Resistance | $R_{L(PULLUP)}$ | Output current $\geq -10\text{ mA}$ | 1.2 | – | – | k Ω |
| Output Saturation Voltage | $V_{OUT(Sat)LOW}$ | Output current = -4.7 mA , $V_{CC} = 5\text{ V}$, Output FET on | – | – | 0.35 | V |
| Output Current Limit | I_{LIMIT} | Output FET on, $T_A = 25^\circ\text{C}$ | 20 | 30 | 50 | mA |
| Output Zener Clamp Voltage | V_{ZOUT} | $T_A = 25^\circ\text{C}$, output current = -3 mA | 20 | – | – | V |
| Internal Load Capacitor [3] | C_{LI} | $T_A = 25^\circ\text{C}$ | – | 1.5 | – | nF |
| External Load Capacitor | C_{LX} | | – | – | 4.7 | nF |

Continued on the next page...

OPERATING CHARACTERISTICS (continued): Valid T_A and V_{CC} , unless otherwise specified

| Characteristics | Symbol | Test Conditions | Min. | Typ. | Max. | Unit |
|--|--------------------|---|------|------|------|------|
| Output Response Time ^[4] | t_{resp} | bw_sel_c = 4-7 | – | 0.15 | – | ms |
| | | bw_sel_c = 3 | – | 0.25 | – | ms |
| | | bw_sel_c = 2 | – | 0.69 | – | ms |
| | | bw_sel_c = 1 | – | 2.4 | – | ms |
| | | bw_sel_c = 0 | – | 9.3 | – | ms |
| Power-On Time ^[4] | t_{PO} | bw_sel_c = 4-7 | – | 0.6 | – | ms |
| | | bw_sel_c = 3 | – | 0.75 | – | ms |
| | | bw_sel_c = 2 | – | 1.25 | – | ms |
| | | bw_sel_c = 1 | – | 3.7 | – | ms |
| | | bw_sel_c = 0 | – | 13 | – | ms |
| Output Jitter, PWM ^[1] | PWM _{JIT} | outmsg_mode = 0, SENT_PWM_RATE < 2 kHz | –1 | – | 1 | LSB |
| | | outmsg_mode = 0, SENT_PWM_RATE ≥ 2 kHz | –3 | – | 3 | LSB |
| Output, Integral Nonlinearity | INL | outmsg_mode = 0, SENT_PWM_RATE < 2 kHz | – | ±0.5 | – | %FSO |
| Maximum Output Resolution ^[5] | OUT _{RES} | $T_A = 25^\circ\text{C}$, outmsg_mode = 1-5 | – | 12 | – | bit |
| | | $T_A = 25^\circ\text{C}$, outmsg_mode = 0, SENT_PWM_RATE ≤ 2 kHz | – | 12 | – | bit |
| PWM Carrier Frequency ^[6] | f_{PWM} | | –15 | – | 15 | % |

[1] Determined from design characterization; not tested in production.

[2] Noise (Peak-to-Peak) calculated as 6 sigma (6 standard deviations) from characterization of a small sample of devices. Conversion of noise from gauss to LSB can be done by: Noise (G) × Sensitivity (LSB/G) = Noise (LSB)

[3] Capacitor internal to device package between V_{OUT} and GND. Capacitor specifications are determined by the manufacturer.

[4] Defined as time before magnetic data is 90% of the settled value.

[5] When outmsg_mode = 0, the maximum output resolution decreases to 11 – n (bits) for SENT_PWM_RATE = 2 kHz × 2ⁿ.

[6] PWM carrier frequency accuracy is % of the programming target. See programmable parameter reference for PWM carrier frequency programming options.




Figure 1: V_{CC} Thresholds and Resultant Output States

MAGNETIC CHARACTERISTICS: Valid at $T_A = 25^\circ\text{C}$ and $V_{CC} = 5\text{ V}$, unless otherwise specified

| Characteristics | Symbol | Test Conditions | Min. | Typ. | Max. | Unit ^{[1][2]} |
|--------------------------|--------------------|-------------------------------|-------|--------|------|------------------------|
| Input Field Range | B_{IN} | | -1500 | - | 1500 | G |
| Initial Sensitivity | $SENS_{INIT}$ | | - | 0.0333 | - | %FSO/G |
| Initial Quiescent Output | QO_{INIT} | | - | 50 | - | %FSO |
| Initial Output Clamp | $OUT_{CLP(L)INIT}$ | clamp = 0, outmsg_mode = 1-5 | - | 0 | - | LSB |
| | | clamp = 0, outmsg_mode = 0 | - | 2 | - | %D |
| | $OUT_{CLP(H)INIT}$ | clamph = 0, outmsg_mode = 1-5 | - | 4095 | - | LSB |
| | | clamph = 0, outmsg_mode = 0 | - | 98 | - | %D |

[1] 1 G (gauss) = 0.1 mT (millitesla).

[2] FSO means Full Scale Output. See Definitions of Terms section.

ACCURACY CHARACTERISTICS: Valid at T_A and V_{CC} , unless otherwise specified

| Characteristics | Symbol | Test Conditions | Min. | Typ. | Max. | Unit ^{1,2} |
|---|----------------------|--|-------|------------|------|---------------------|
| Lifetime Sensitivity Drift | $\Delta SENS_{LIFE}$ | Variation on final programmed Sensitivity value; $T_A = 25^\circ C$ coilcomp_dis = 0; shift after AEC-Q100 grade 0 qualification testing; measured at $T_A = 25^\circ C$ | - | $<\pm 1.5$ | - | % |
| | | Variation on final programmed Sensitivity value; $T_A = 25^\circ C$ coilcomp_dis = 1; shift after AEC-Q100 grade 0 qualification testing; measured at $T_A = 25^\circ C$ | - | $<\pm 2.5$ | - | % |
| Sensitivity Drift Due To Package Hysteresis | $\Delta SENS_{PKG}$ | Variation on final programmed Sensitivity value; measured at $T_A = 25^\circ C$ after temperature cycling from $25^\circ C$, coilcomp_dis = 0 | - | $<\pm 0.5$ | - | % |
| | | Variation on final programmed Sensitivity value; measured at $T_A = 25^\circ C$ after temperature cycling from $25^\circ C$, coilcomp_dis = 1 | - | $<\pm 2.0$ | - | % |
| Sensitivity Drift Over Temperature ^[1] | $\Delta SENS$ | $25^\circ C \leq T_A \leq 150^\circ C$, coil compensation on | -1.5 | - | 1.5 | % |
| | | $-40^\circ C \leq T_A \leq 25^\circ C$, coil compensation on | -2 | - | 2 | % |
| | | $25^\circ C \leq T_A \leq 150^\circ C$, coil compensation off | -1 | - | 1 | % |
| | | $-40^\circ C \leq T_A \leq 25^\circ C$, coil compensation off | -1.5 | - | 1.5 | % |
| Quiescent Output Drift ^[2] | ΔQO | $SENS = SENS_{INIT}$ | -1.32 | - | 1.32 | G |

[1] Does not include drift over lifetime and package hysteresis.

[2] Quiescent Output Drift scales with Sensitivity.




Figure 2: Typical Initial Sensitivity Drift Due To Temperature and Package Hysteresis

PROGRAMMABLE CHARACTERISTICS: Valid at $T_A = 25^\circ\text{C}$ and $V_{CC} = 5\text{ V}$, unless otherwise specified

| Characteristics | Symbol | Test Conditions | Min. | Typ. | Max. | Unit [1] |
|--|------------------------------------|---|--------|------|-------|----------------------|
| SENSITIVITY | | | | | | |
| Output Sensitivity Trim Range [2] | SENS | | 0.5 | – | 48 | – |
| Bits Sensitivity Trim, Coarse | Bit (SENSM_C) | | – | 3 | – | bit |
| Sensitivity Coarse Trim Range [3] | SENSM_C | | 1 | – | 32 | – |
| Bits Sensitivity Trim, Fine | Bit (SENS_C) | | – | 11 | – | bit |
| Sensitivity Fine Trim Range [4] | SENS_C | | 0.5 | – | 1.5 | – |
| Bits Sensitivity Polarity | Bit (POL) | | – | 1 | – | bit |
| OFFSET (QUIESCENT OUTPUT) | | | | | | |
| Bits Quiescent Output Trim, Fine | Bit (QO_C) | | – | 16 | – | bit |
| Customer Quiescent Output Fine Trim Range | QO_C | | –32768 | – | 32767 | LSB |
| CLAMPS (HIGH AND LOW OUTPUT CLAMPS) | | | | | | |
| Bits Output Low Clamp | Bit (OUT _{CLP} (LOW)) | | – | 12 | – | bit |
| Output Low Clamp Range | OUT _{CLP} (LOW) | | 0 | – | 4095 | LSB |
| Bits Output High Clamp | Bit (OUT _{CLP} (HIGH)) | | – | 12 | – | bit |
| Output High Clamp Range | OUT _{CLP} (HIGH) | | 0 | – | 4095 | LSB |
| TEMPERATURE COMPENSATION | | | | | | |
| Bits 1 st Order Sensitivity TC | Bit (SENSTC1) | senstc1_hot_c, senstc1_cld_c | – | 11 | – | bit |
| 1 st Order Sensitivity TC Range | SENSTC1 | $25^\circ\text{C} < T_A \leq 150^\circ\text{C}$ | –0.391 | – | 0.391 | % / °C |
| | | $-40^\circ\text{C} \leq T_A < 25^\circ\text{C}$ | –0.781 | – | 0.781 | % / °C |
| Bits 2 nd Order Sensitivity TC | Bit (SENSTC2) | senstc2_hot_c, senstc2_cld_c | – | 10 | – | bit |
| 2 nd Order Sensitivity TC Range | SENSTC2 | $25^\circ\text{C} < T_A \leq 150^\circ\text{C}$ | –1.5 | – | 1.5 | m% / °C ² |
| | | $-40^\circ\text{C} \leq T_A < 25^\circ\text{C}$ | –6 | – | 6 | m% / °C ² |
| Bits 1 st Order Offset TC | Bit (QOTC) | qotc_hot_c, qotc_cld_c | – | 12 | – | bit |
| 1 st Order Offset TC Range | QOTC | $25^\circ\text{C} < T_A \leq 150^\circ\text{C}$ | –32 | – | 31.98 | LSB / °C |
| | | $-40^\circ\text{C} \leq T_A < 25^\circ\text{C}$ | –64 | – | 63.97 | LSB / °C |

Continued on the next page...

PROGRAMMABLE CHARACTERISTICS (continued): Valid at $T_A = 25^\circ\text{C}$ and $V_{CC} = 5\text{ V}$, unless otherwise specified

| Characteristics | Symbol | Test Conditions | Min. | Typ. | Max. | Unit [1] |
|---|---------------------------------|-----------------|-------|------|------|------------|
| LINEARIZATION | | | | | | |
| Linearization Positions | | | – | 17 | – | data point |
| Bits Linearization Coefficients | Bits (LIN _{COEF}) | | – | 12 | – | bit |
| Bits Post Linearization Sensitivity Trim | Bits (PLIN _{SENS}) | | – | 12 | – | bit |
| Post Linearization Sensitivity Trim Range | PLIN _{SENS} (RANGE) | | – | ±1 | – | – |
| Bits Post Linearization Offset Trim | Bits (PLIN _{QVO}) | | – | 12 | – | bit |
| Post Linearization Offset Trim Range | PLIN _{QVO} (RANGE) | | –2048 | – | 2047 | LSB |
| Bit Linearization Output Polarity | Bits (POL _{OUT}) | | – | 1 | – | bit |
| Bit Linearization Input Polarity | Bits (POL _{IN}) | | – | 1 | – | bit |

[1] 1 G (gauss) = 0.1 mT (millitesla).

[2] The Initial Sensitivity is adjustable by the Sensitivity Trim Coarse and Fine parameters. When reducing the initial Sensitivity check the input field is within the range specified by B_{IN} .

[3] Sensitivity Coarse Trim is a multiplier to the initial Sensitivity with step sizes defined by the sensm parameter. Refer to the Programmable Parameter Reference section for more information.

[4] Sensitivity Fine Trim is a multiplier applied to the initial Sensitivity after the Sensitivity Coarse Trim with step sizes defined by the sens_c parameter. Refer to the Programmable Parameter Reference section for more information.

APPLICATION INFORMATION

Signal Path

The A1342 contains a Hall-effect transducer that produces a signal proportional to the magnetic flux density perpendicular to the face of the package, referred as the applied magnetic flux density. The output of the Hall transducer is then amplified and digitized. The resulting signal is a signed digital value that can be scaled, offset, and compensated to achieve a desired output. The advanced digital parameters allow for a large range of input signals to be adjusted for the application. This results in the A1342 being highly flexible and accurate for applications with challenging sensing requirements. The following sections give an overview of digital signal path blocks and the corresponding transfer functions.

COMPENSATION BLOCK

The compensation block contains adjustments to the Sensitivity and Offset. This includes compensation for input signal changes over the operating temperature range. First, the Sensitivity Trim Block multiplies the signal by a temperature-dependant gain (or attenuation) factor. The correction is segmented into two regions: hot and cold, where hot indicates ambient temperatures greater or equal to 25 °C, and cold indicates ambient temperatures lesser or equal to 25 °C. Each segmented region also contains 1st and 2nd order Sensitivity temperature compensation.

Note:

The hot Sensitivity temperature compensation is independent of the cold region.

Equations 1 and 2 show the transfer function of the Sensitivity Trim Block.

$$Y_1 = B_{IN} \cdot SENS_{INT} \cdot POL_C \cdot SENSM_C \cdot SENS_C \cdot \left[1 + \left(\left(\frac{SENSTC2_HOT_C}{1000} \right) \cdot \Delta T_A + SENSTC1_HOT_C \right) \cdot \frac{\Delta T_A}{100} \right] \quad (1)$$

$$Y_2 = B_{IN} \cdot SENS_{INT} \cdot POL_C \cdot SENSM_C \cdot SENS_C \cdot \left[1 + \left(\left(\frac{SENSTC2_CLD_C}{1000} \right) \cdot \Delta T_A + SENSTC1_CLD_C \right) \cdot \frac{\Delta T_A}{100} \right] \quad (2)$$

NOTE:

Included in the transfer function shown in Equations 1 and 2 is the conversion from the applied magnetic input to a digital value, $B_{IN} \times SENS_{INT}$.

The output of the Sensitivity Trim Block, Y_1 , is a 17-bit signed integer.

The Offset Trim Block adds a temperature-dependent factor to the input signal. The offset factor is segmented into two region: hot and cold, as defined in the Sensitivity Trim Block. Each segment contains 1st order Offset temperature compensation. Equations 3 and 4 show the transfer functions of the Offset Trim Block. The output, Y_2 , is a 13-bit signed integer and is the value passed out of the Compensation Block.

$$Y_2 = Y_1 + QO_C + QOTC_HOT_C \times \Delta T_A \quad (3)$$

$$Y_2 = Y_1 + QO_C + QOTC_CLD_C \times \Delta T_A \quad (4)$$




Figure 3: Compensation Block

Table 1: Compensation Block Parameters

| Variable | Description | Programmable Parameter (Memory Location) | Units |
|---------------|--|--|--------------------|
| POL_C | Determines the sensitivity polarity. The default polarity is increasing with output with increasing applied south magnetic flux density. | pol_c (Register sens_trim_c 0x3 [15]) | NA |
| SENSM_C | Coarse Sensitivity multiplier | sensm_c (Register sens_trim_c 0x3 [14:12]) | NA |
| SENS_C | Fine Sensitivity multiplier | sens_c (Register sens_trim_c 0x3 [10:0]) | NA |
| SENSTC2_HOT_C | 2 nd order Sensitivity temperature compensation for $T_A \geq 25^\circ\text{C}$ | senstc2_hot_c (Register senstc2_c 0x5 [9:0]) | m%/°C ² |
| SENSTC1_HOT_C | 1 st order Sensitivity temperature compensation for $T_A \geq 25^\circ\text{C}$ | senstc1_hot_c (Register senstc1_c 0x4 [10:0]) | %/°C |
| SENSTC2_CLD_C | 2 nd order Sensitivity temperature compensation for $T_A \leq 25^\circ\text{C}$ | senstc2_cld_c (Register senstc2_c 0x5 [21:12]) | m%/°C ² |
| SENSTC1_CLD_C | 1 st order Sensitivity temperature compensation for $T_A \leq 25^\circ\text{C}$ | senstc1_cld_c (Register senstc1_c 0x4 [22:12]) | %/°C |
| ΔT_A | Change in ambient temperature, equal the ambient temperature, T_A , minus 25°C . | NA | °C |
| QO_C | Fine quiescent output adjustment | qo_c (Register qo_trim_c 0x6 [15:0]) | LSB |
| QOTC_HOT_C | 1 st order quiescent output temperature drift compensation. | qotc_hot_c (Register qotc_c 0x7 [11:0]) | LSB/°C |
| QOTC_CLD_C | 1 st order quiescent output temperature drift compensation. | qotc_cld_c (Register qotc_c 0x7 [23:12]) | LSB/°C |
| SENS_INIT | Initial Sensitivity | NA | LSB/G |
| B_{IN} | Applied magnetic flux density | NA | G |

LINEARIZATION

The Linearization block passes the output from the compensation block through a piecewise-linear transfer described by 17 points, which define 16 line segments. The x -coordinates of these points are programmable and are stored as 12-bit words in a table in memory, LIN_C. Corresponding y -coordinates are fixed and are equally spaced over the output range. For proper operation, table increasing entries, i.e., $x_0 \leq x_1 \leq x_2 \leq \dots \leq x_{16}$ should be satisfied. If not satisfied, the output is undefined. Adjacent table entries can be equal. The linearization algorithm will not produce output values in between the y -coordinates that correspond to identical adjacent table entries; these output values are skipped. Thus jumps in the transfer function can be realized. Additionally, two more segments are implemented above and below the normal 12-bit output range to facilitate use of all 16 linearization segments without output clipping. Output points in these two seg-

ments are linearly extrapolated from the two points nearest each end of the linearization table.

The linearization algorithm incorporates two modes, linearization mode (Lin Mode) and binning mode (Bin Mode).

Linearization Mode (Lin Mode)

Figure 4 shows an example transfer function which is monotonically increasing. Adjacent points form line segments; input values between are linearly interpolated to find intermediate values. Input values smaller than the first table entry are extrapolated using the points $(x_0, -2048)$ and $(x_1, -1792)$, down to a minimum output value of -2304 . Input values larger than the last table entry are extrapolated using the points $(x_{15}, +1792)$ and $(x_{16}, +2048)$, up to a maximum output value of $+2304$. The output of the Linearization Algorithm Block, Y_3 , is a 13-bit signed integer.




Figure 4: Monotonically Increasing Linearization Transfer Function

Linearization Binning Mode (Bin Mode)

When the `bin_mode_c` parameter, address `lin8_c 0x12` [13], is set, the linearization algorithm does not interpolate between points, but instead produces the output corresponding to the nearest linearization table entry less than or equal to the input value. This transfer function is useful for applications that require distinguishing between several different input ranges. For example, see Figure 5, because $x_2 = x_3 = x_4$ and corresponding output points are -1536 , -1280 and -1024 respectively, input values just below $x_2 = x_3 = x_4$ produce an output of -1792 (output corresponding to x_1) and inputs just above or equal to $x_2 = x_3 = x_4$ produce an

output of -1024 . Intermediate values are skipped. Thus the linearization table functions like a series of comparators with 12-bit programmable thresholds.

Note:

The input values below the lowest table entry produce an output value of -3072 , while input values above the highest table entry produce an output value of $+2048$.




Figure 5: Bin Mode Transfer Function Containing Jumps (Identical Adjacent Table Entries)

The Linearization coefficients and corresponding parameters are stored in following memory locations.

Table 2: Linearization Algorithm Block Parameters

| Coefficient/Parameter | Description | Memory Location | Units |
|-----------------------------------|--|--------------------------------|-------|
| $x_0, x_2, \dots, x_{14}, x_{16}$ | Even Linearization Coefficients | <code>lin0_c ... lin8_c</code> | LSB |
| $x_1, x_3, \dots, x_{13}, x_{15}$ | Odd Linearization Coefficients | <code>lin0_c ... lin7_c</code> | LSB |
| <code>lint_e</code> | Set to logic 1 to enable the Linearization table. | <code>lin8_c 0x12</code> [12] | NA |
| <code>lint_bin_e</code> | Set to logic 1 to enable linearization binning mode. | <code>lin8_c 0x12</code> [13] | NA |
| <code>lint_out_inv</code> | Set to logic 1 to Invert output of linearization block | <code>lin8_c 0x12</code> [14] | NA |
| <code>lint_in_inv</code> | Set to logic 1 to Invert input of linearization block | <code>lin8_c 0x12</code> [15] | NA |

POST-LINEARIZATION TRIM

An additional gain and offset trim stage is available in the linearization block. This can be used to attenuate and gain the signal to maintain usage of all 17 linearization points when using an output range that is not full-scale. Equation 5 shows the transfer function for the Post Linearization. The output of the Post Linearization Block, Y_4 , is a 12-bit signed integer and is the output of the Linearization Block.




Figure 6: Linearization Block

$$Y_4 = Y_3 \times (1 + PLIN_SENS) + PLIN_QVO \quad (5)$$

CLAMP

The clamp block limits the output to a programmable range set by the parameters clamph and clampl, register clamp_c 0x8. Clamps are programmable throughout the full output range. If the input to the clamp block is greater than the value set by clamph the output is limited to the upper clamp value. Similarly, if the input to the clamp block is less than the value set by clampl the output is limited to the lower clamp value. If the lower clamp exceeds the upper clamp the output is undefined.

Table 3: Post-Linearization Trim Memory Parameters

| Variable | Step Size | Min. | Max. | Description | Parameter (Memory Location) | Units |
|-----------|------------------|-------|-------|--|-------------------------------------|-------|
| PLIN_SENS | 2 ⁻¹¹ | -1 | +1 | Customer post-linearization sensitivity adjustment | plin_sens, (post_lin_c 0x13 [11:0]) | NA |
| PLIN_QVO | 1 | -2048 | +2047 | Customer post-linearization offset adjustment | plin_qvo, (post_lin_c 0x13 [23:12]) | LSB |

Table 4: Clamp Block Parameters

| Variable | Description | Programmable Parameter (Memory Location) | Units |
|----------|----------------------------------|--|-------|
| CLAMPH | Determines the upper clamp value | clamph (Register clamp_c 0x8 [11:0]) | LSB |
| CLAMPL | Determines the lower clamp value | clampl (Register clamp_c 0x8 [23:12]) | LSB |

Note:

The input to the clamp block is a 12 bit signed value (-2048 to +2047) and is changed to a 12 bit unsigned value (0 to 4095) before comparing to the upper and lower clamp values.

Equations 6 and 7 show the transfer functions for the clamp block. The output of the Clamp Comparison is a 12-bit unsigned integer and is passed to the output block at a fixed frequency of 16 kHz.




Figure 7: Clamp Block

$$Y_5 = Y_4 + 2048$$

(conversion from signed to unsigned) (6)

$$\text{if } (Y_5 > OUT_{CLP(HIGH)}), \text{ then } Y_6 = OUT_{CLP(HIGH)}$$

$$\text{else if } (Y_5 < OUT_{CLP(LOW)}), Y_6 = OUT_{CLP(LOW)}$$

$$\text{else } Y_6 = Y_5 \quad (7)$$

Diagnostic Conditions

DIAGNOSTIC MODES

The A1342 contains features specifically designed to reduce nondetectable fault conditions and improve system-level ASIL (Automotive Safety Integrity Level) performance. The diagnostic features provide ability to diagnose errors of the main signal path, including the analog signal path (Hall sensor and amplifiers), the ADC, and the digital processing. The A1342 also contains features to diagnose broken wire or open circuit conditions. A description of the broken wire fault conditions are listed in Table 5.

DIAGNOSTIC CONFIGURATION

The A1342 contains EEPROM parameters to configure the diagnostic modes and output behavior. The EEPROM register, `cfg_c`, contains configurable parameters to enable or disable the Overvoltage Detection, Undervoltage Detection, BIST Error, Signal Out of Range, and Analog Signal Path Error (CoilBIST). In addition the output behavior in response to the error conditions is configurable. By default the device outputs a diagnostic error signal that is decoded by either the PWM or SENT message. Alternatively, the output behavior in response to the error conditions can be set to a high-impedance state (see Table 7).




Figure 8: Diagnostic Application Circuit

ANALOG SIGNAL PATH

Errors in the analog signal path are diagnosed using an integrated active coil compensation circuit, CoilBIST. When enabled (`coil_freq < 3`), an active coil provides a known diagnostic input magnetic field to the Hall sensor circuit. The diagnostic input runs passively during normal operation and does not interfere with the response to external magnetic input. The analog signal path is time-shared between the diagnostic input and the external input at a rate of approximately 128 kHz. The CoilBIST signal detection circuit monitors the signal path at rate of approximately 8 kHz by comparing the diagnostic signal to an internal reference. In the event the analog signal path deviates by more than 10%, V_{OUT} is forced to a state defined by the EEPROM register `cfg_c`. Setting the parameter `coilbist_dis = 1` prevents the analog signal path monitoring from reporting detected errors on the output.

The active coil also provides compensation to reduce Sensitivity drift from lifetime and package stress influences. This feature results in a highly stable Sensitivity over multiple temperature excursions. A programmable bit, `coilcomp_dis`, is available to disable the compensation while retaining the diagnostic features.

The active coil compensation feature requires an increase of the supply current, I_{CC} , to generate the internal diagnostic magnetic input. The coil compensation on-time is fixed at approximately 16 ms, while the off-time is determined by the EEPROM parameter `coil_freq`. When the coil compensation is on, the supply current increases by approximately 4 mA. See Table 6 for available coil compensation off time settings. Note, setting `coil_freq` to a value of 1 or 2 may increase Noise. Setting `coil_freq` to a value of 3 disables the active coil compensation and diagnostic features during normal operation, while this may reduce noise.

Table 5: Broken Wire Detection Conditions

| Description | Circuit | S1 | S2 | S3 | VOUT | VOC |
|---------------|----------|--------|--------|--------|----------------|-----|
| Broken VCC | Figure 8 | OPEN | CLOSED | CLOSED | High Impedance | VCC |
| Broken VOUT | Figure 8 | CLOSED | OPEN | CLOSED | Low Impedance | VCC |
| Broken Ground | Figure 8 | CLOSED | CLOSED | OPEN | High Impedance | VCC |

NOTE: For proper diagnostic detection the device output clamps should be programmed to appropriate levels. Typical levels are 10% FSO for clamp low and 90% FSO for clamp high.

Table 6: Coil Compensation On/Off Time

| coil_freq ^[1] (0x09 bits 14:13) | Typical Coil Compensation On-Time (ms) | Typical Coil Compensation Off-Time (ms) | Typical Average I _{CC} Increase Due to Coil Compensation (mA) | CoilBIST Response Time (ms) |
|---|--|---|--|-----------------------------|
| 0 | 16 | 0 | 4 | 10 |
| 1 | 16 | 16 | 2 | 26 |
| 2 | 16 | 4080 | 0.015625 | 4090 |
| 3 | 0 | 16 | NA | After BIST Request |

^[1] Setting coil_freq = 1 or 2 may increase noise. Setting coil_freq = 3 may decrease noise but increase Lifetime Sensitivity Drift.

BIST

The A1342 also has a BIST (Built-In Self Test) feature to check for logic errors in the digital processing circuitry. The BIST feature is configurable with options to disable or enable on request. The options are configured by customer-programmable EEPROM bits in the cfg_c register. When set for enable on request, the BIST runs in response to a request by an external controller. Diagnostic request will be different based on the output protocol. When the output protocol is PWM or SENT, the controller must hold the output low for two consecutive messages to trigger a BIST. In the case when output protocol is TSENT, to request the device perform a BIST, the external controller must hold the output low for a period of time, t_{dreq}, during the Data Nibbles of the output after the SCN nibble (see Table 8, Figure 11, and Figure 15), and then release the output to a high-impedance state. For SSENT and ASENT, the F_DIAG function pulse should be used to trigger a BIST request.

Alternatively, the BIST can execute in response to a write command from the serial communication interface. To request the device perform a BIST using the serial communication interface, a write command is used to set parameter lbist_run = 1 in register

lbist_ctrl_c (see Figure 28). The LBIST test takes approximately 10 ms to complete.

After the BIST request is received, the Output remains in a high-impedance state while the internal BIST executes. If the parameter lbist_ack is set, the first output message contains a BIST signature value (LBIST Ack) indicating whether or not an error is detected during the digital logic test. If the parameter coilbist_ack is set, the first output message contains the coil diagnostic value (ABIST Ack) from the CoilBIST. If both lbist_ack and coilbist_ack are set, the first output message is the LBIST Ack followed by the second output message ABIST Ack. The ABIST Ack message is only valid when coil_freq = 3. For more information on CoilBIST when using coil_freq < 3, see Diagnostic Conditions: Analog Signal Path. If there are no errors detected, the next output message after the acknowledge messages contains the normal output response. Alternatively, the LBIST Ack and ABIST Ack are returned in register lbist_ctrl_c. Should an error be detected, the output remains in a high-impedance state after the acknowledge messages are transmitted. See Table 7, Diagnostic Summary Table, for more information on the output in response to a diagnosed error.




Figure 9: Acknowledgment Signatures for BIST (no errors detected)

(CO = Calibrated Output, valid when coil_freq = 3)

SIGNAL OUT OF RANGE

Included in the A1342 is a diagnostic feature, Signal Out of Range, to detect erroneous clamping of digital signal path as a result of external magnetic input signals. This feature also checks that the magnetic input does not exceed internal ADC range. The output responds to a Signal Out of Range diagnostic according to the settings in the EEPROM register, `cfg_c` and Table 7.

UNDERVOLTAGE DETECTION AND RESET

The A1342 contains circuitry to detect a condition when the supply voltage drops below the specified limit. Hysteresis is designed into the circuit to prevent chattering around the threshold. This hysteresis is defined by $V_{CC(UV)HIGH} - V_{CC(UV)LOW}$. As an example, initially V_{CC} and V_{OUT} are within the normal operating range. If V_{CC} drops below $V_{CC(UV)LOW}$, V_{OUT} is forced to a state defined by the EEPROM register, `cfg_c`. When V_{CC} returns above $V_{CC(UV)HIGH}$, V_{OUT} returns to its normal operating state. If V_{CC} drops below the internal reset level, $V_{CC(POR)LOW}$, the output is forced to a high-impedance state. When V_{CC} returns above the rising reset level, $V_{CC(POR)HIGH}$, the output responds according to the undervoltage detection. The output will not respond with normal data until a delay of t_{PO} after a reset event.

OVERVOLTAGE DETECTION

The A1342 contains circuitry to detect a condition when the supply voltage rises above the specified limit. Hysteresis is designed into the circuit to prevent chattering around the threshold. This hysteresis is defined by $V_{CC(OV)HIGH} - V_{CC(OV)LOW}$. As an example, initially V_{CC} and V_{OUT} are within the normal operating range. If V_{CC} rises above $V_{CC(OV)HIGH}$, V_{OUT} is forced to a state defined by the EEPROM register, `cfg_c`. When V_{CC} returns below $V_{CC(OV)LOW}$, V_{OUT} returns to its normal operating state.

The overvoltage detection is only enabled when the EEPROM lock bit is set. If the EEPROM lock bit is not set, and V_{CC} increases above $V_{CC(OV)HIGH}$, the device will enter programming mode and the output is forced to a high-impedance state. If V_{CC} rises above the high-voltage threshold, $V_{CC(HV)HIGH}$, the output is forced to a high-impedance state.

OVERTEMPERATURE DETECTION

The A1342 contains circuitry to detect a condition when the ambient temperature is greater than 160°C, which is outside of the operating range of the part. This will cause the output to respond according to the settings in the EEPROM register, `cfg_c` and Table 7.

BROKEN GROUND DETECTION

The A1342 contains circuitry to detect a condition when the ground connection is disconnected. When the ground connection is severed, the digital output driver turns off, forcing the output to a high-impedance state.

EEPROM DIAGNOSTICS

The A1342 contains EEPROM with error checking and correction, ECC. The ECC corrects for a single EEPROM bit error without effecting device performance. The ECC also detects a dual bit EEPROM error and triggers an internal fault signal and forces the output to a high-impedance state. Upon a read of EEPROM with no errors, bits 0 through 25 will return the requested EEPROM contents and bits 26 through 31, the six MSBs of the EEPROM register, will return as all zeros. When a corrected single bit error is detected, bit 28 of the read response will return high, indicating the single bit error. When a dual bit error is detected, a read of EEPROM will have bit 29 set high indicating the dual bit error.

Table 7: Diagnostic Summary Table

| Diagnostic Detection | Conditions | V _{OUT} (PWM) diag_mode = 0 | V _{OUT} (SENT) diag_mode = 0 | V _{OUT} (PWM) diag_mode = 1 ^[1] | diag_reg_c (binary) | SENT Data Nibble #4 and #5 (sent_ data_cfg = 1) (binary) |
|---------------------------------------|---|---|--|--|------------------------|--|
| Overvoltage Condition | Overvoltage detection is enabled, diagnostic output is set for advanced output flag, and device lock is set, ovd_dis = 0, dev_lock = 5. | ½ carrier frequency 60% DC | See SENT, SCN nibble bit 1 = 1 | High impedance | XXX1 XXXX | XXXX 1XXX |
| Undervoltage Condition ^[2] | Undervoltage detection is enabled, and diagnostic output is set for advanced output flag, uvd_dis = 0. | ½ carrier frequency 40% DC | See SENT, SCN nibble bit 1 = 1 | High impedance | XXXX 1XXX | XXX1 XXXX |
| CoilBIST (Analog Signal Path) Error | CoilBIST enabled and diagnostic output is set for advanced output flag, coilbist_dis = 0, coil_freq < 3. | ½ carrier frequency 30% DC | See SENT, SCN nibble bit 0 = 1 | High impedance | XXXX X1XX | XX1X XXXX |
| BIST Error | lbist_dis = 0 | High impedance | High impedance | High impedance | XXXX XX1X | NA (High Impedance) |
| Overtemperature Condition | Overtemperature detection is enabled and diagnostic output is set for advanced output flag, otmp_dis = 0. | ½ carrier frequency 70% DC | See SENT, SCN nibble bit 1 = 1 | High impedance | XX1X XXXX | XXXX X1XX |
| Signal Out of Range, Low | Signal Out of Range detection is enabled, and diagnostic output is set for advanced output flag, oor_dis = 0. | ½ carrier frequency 80% DC | See SENT, SCN nibble bit 1 = 1 | High impedance | X1XX XXXX | XXXX XX1X |
| Signal Out of Range, High | Signal Out of Range detection is enabled, and diagnostic output is set for advanced output flag, oor_dis = 0. | ½ carrier frequency 90% DC | See SENT, SCN nibble bit 1 = 1 | High impedance | 1XXX XXXX | XXXX XXX1 |
| EEPROM Fault (2 bit error detection) | | High impedance | High impedance | High impedance | XXXX XXX1 | NA (High Impedance) |

^[1] diag_mode = 1 is not supported when V_{OUT} is configured for SENT protocol.

^[2] An Overvoltage Condition will cause the device to enter Programming Mode which will result in the output being in a high-impedance state when dev_lock does not equal 5.

Linear Output Protocols

The A1342 operating output is a digital voltage signal that transfers information proportionally to the applied magnetic input signal. Few customer-selectable options are provided for output signal formatting: pulse-width-modulated (PWM), and variations of single-edge nibble transmission encoding scheme (SENT, SAEJ2716).

Note:

The device response to the applied magnetic field is on the OUT pin. However, that pin is also used to transmit and receive data in response to a serial programming commands, during which the normal output operation is suppressed. Refer to the Programming Serial Interface section for more information. The EEPROM is described in the EEPROM Structure section. The output falling edge slew rate is adjustable using the outdrv_sel parameter. Adjusting this can improve EMC performance by reducing high-frequency

currents. This parameter can also increase the output fall time and result in longer minimum pulse durations for serial communication or SENT transmission.

PWM OUTPUT MODE (outmsg_mode = 0)

PWM involves converting the output voltage amplitude to a series of constant-frequency binary pulses, with the percentage of the of high portion of the pulse varied in direct proportion to the applied magnetic field.

The PWM output mode is configured by setting the following parameters in EEPROM:

- PWM option is EEPROM programmable (for programming parameters, see EEPROM Structure section)
- sent_pwm_rate sets the PWM carrier frequency based on the values in Table 14




Figure 10: PWM Mode Duty-Cycle-Based Waveform

PWM mode outputs a duty-cycle-based waveform that can be read by the external controller as a cumulatively changing continuous voltage.

Initiation of the BIST is done through the external controller request and explained in Table 8 and Figure 11.

Table 8: External BIST Request and SENT Trigger Characteristics

| Parameter | Symbol | Description | Min. | Typ. | Max. | Unit |
|--|----------------------|--|------|------|------|---------------------------|
| Trigger Pulse Width | t_{trg} | Trigger pulse for TSENT operation; see SSENT and ASENT sections for F_OUTPUT pulse durations | 1.8 | – | – | μ s |
| Synchronization Pulse Delay ^[1] | t_{dsync} | | 7 | – | 524 | tick |
| SENT Output Trigger Signal | $V_{SENTtrig(L)}$ | V_{OUT} falling, $T_A = 25^\circ\text{C}$ | – | – | 1.39 | V |
| | $V_{SENTtrig(H)}$ | V_{OUT} rising, $T_A = 25^\circ\text{C}$ | 2.3 | – | – | V |
| SENT Output Trigger Signal Hysteresis | $V_{SENTtrig(HYST)}$ | $T_A = 25^\circ\text{C}$ | – | 300 | – | mV |
| External BIST Request Pulse Width | t_{dreq} | PWM | 2 | – | – | frame rate ^[2] |
| | | SENT Modes | 15 | – | – | tick |
| BIST Delay | t_{diag} | Delay for device to execute internal BIST | 10 | – | 20 | ms |

^[1] t_{dsync} can increase from 7 ticks to preserve a minimum time of approximately 70 μ s from the falling edge of the trigger to the start of the SCN nibble.

^[2] The frame rate is determined by the sent_pwm_rate parameter.

^[3] When in Trigger SENT Output mode the external controller must pull the output low after t_{dsync} and before the first data nibble in the SENT frame, for a time of t_{dreq} , to initiate a BIST request.




Figure 11: External BIST Request with PWM or Synchronous SENT Output Mode

SENT OUTPUT MODES

The SENT output mode converts the input magnetic signal to a binary value mapped to the Full Scale Output, FSO, range of 0 to 4095, shown in Figure 12. This data is inserted into a binary pulse message, referred to as a frame, that conforms to the SENT data transmission specification (SAEJ2716 JAN2010). Certain parameters for configuration of the SENT messages can be set in EEPROM.

The SENT output modes are selected by setting the following parameters in EEPROM:

- SAE J2716 SENT with enhancement options (outmsg_mode = 1)
- Triggered SENT – TSENT (outmsg_mode = 2) – User defines sampling and data retrieving.
- Sequential SENT – SSENT – User requests data from multiple devices on the SENT line in sequential order (outmsg_mode = 4 for short_trigger and outmsg_mode = 3 for long_trigger). Short and long trigger modes can be differentiated on the length and number of host function/request pulses.
- Addressable SENT – ASENT – User requests data from any device on the SENT line in any order. (outmsg_mode = 7, 6, or 5)
- Additional configuration parameters in register 0x14, out_cfg_c.

MESSAGE STRUCTURE

A SENT message is a series of nibbles, with the following characteristics:

- Each nibble is an ordered pair of a low-voltage interval followed by a high-voltage interval
- The low interval, SENT_FIXED, is defined as 5 SENT ticks. The high interval contains information and is variable in duration to indicate the data payload of the nibble.

The duration of a nibble is denominated in clock ticks. The period of a tick is set by sent_pwm_rate parameter as in Table 14. The duration of the nibble is the sum of the low-voltage interval plus the high-voltage interval.

The nibbles of a SENT message are arranged in the following required sequence (see Figure 13):

1. Synchronization and Calibration: flags the start of the SENT message
2. Status and Communication: provides A1342 status and the format of the data
3. Data: magnetic field and optional data
4. CRC: error checking
5. Pause Pulse: sets timing relative to A1342 updates




Figure 12: SENT Mode Output
SENT mode outputs a digital value that can be read by the external controller




Figure 13: General Format for SENT Message Frame

OPTIONAL SHORT SERIAL MESSAGE

The A1342 SENT output supports an optional mode to transmit additional data. The slow serial mode, enables transmission of additional data by encoding information in the Status and Communication (SCN) nibbles. The encoded data is captured over several transmissions and is then decoded to indicate additional short serial message data. For more details on the short serial

message please refer to the SENT SAEJ2716 specification. The slow serial mode is enabled when the EEPROM parameter `sent_slow_ser_dis = 0`. Following a reset, the first message transmitted is 0, following in order of the message ID until message 4, and then repeating. Table 10 identifies the data sent with each message ID. The CRC for the Short Serial Message is derived for the Message ID and data, and is the same checksum algorithm used for the SENT CRC.

Table 9: Short Serial Message Format in SENT Status and Communication Nibble

| SCN Bit (For the values of bits 0 and 1 please see Table 7: Diagnostic Summary) | Nibble # | | | | | | | | | | | | | | | |
|---|------------|---|---|---|------|---|---|---|---|----|-----|----|----|----|----|----|
| | 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11 | 12 | 13 | 14 | 15 | 16 |
| Bit 3 (Start Bit) | 1 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 |
| Bit 2 (Serial Data) | Message ID | | | | Data | | | | | | CRC | | | | | |

Table 10: SENT Slow Serial Data

| Message ID | Data |
|------------|---|
| 0 | Error status from the parameter <code>diag_reg_c</code> located in register <code>err_status_c</code> , 0x45 bits [23:16]. {EEPROM DBE, LBIST, Coil Measurement Monitor, Undervoltage, Overvoltage, Overtemperature, Signal out of range low, Signal out of range high} |
| 1 | 8-bit temperature value from internal temperature sensor. Values are saturated to $\pm 128^{\circ}\text{C}$, and 3 LSBs are rounded to nearest degree |
| 2 | <code>id_c[7:0]</code> (Customer ID, EEPROM 0x2) |
| 3 | <code>id_c[15:8]</code> (Customer ID, EEPROM 0x2) |
| 4 | <code>id_c[23:16]</code> (Customer ID, EEPROM 0x2) |

In the case of SSENT and ASENT mode, SCN bits 2 and 3 can be selected to label the address of the sensor on the shared SENT line (`sen_no_smsg = 1` and `sent_slow_ser_dis = 1`, gives ID in SCN).

DATA NIBBLE FORMAT

The A1342 SENT output supports options for the message data nibble format. The data nibble format is determined by the EEPROM parameter `sent_data_cfg`. The options for either a minimum 3 or maximum 6 nibbles of data is defined in Table 11.

Where:

- `magout[11:0]`: 12-bit magnetic output data.

- `count[11:0]`: SENT frame count. The counter increments once for every frame that is sent up to the maximum count. At the next count, after the maximum, the counter starts again at 0. The maximum count is 15 and 4095 for `sent_data_cfg = 1` and `sent_data_cfg = 2` respectively.
- `temp_out[11:0]`: 12-bit signed output from the internal temperature sensor. Ambient temperature ($^{\circ}\text{C}$) = 12-bit signed temperature value / 8 (LSB / $^{\circ}\text{C}$) + 25.
- `diag[7:0]` Diagnostic flags, EEPROM, LBIST, CoilBist, Undervoltage, Overvoltage, Overtemperature, Signal out of range low, and Signal out of range high.

Table 11: SENT Data

| sent_data_cfg | Data Nibble #1 | Data Nibble #2 | Data Nibble #3 | Data Nibble #4 | Data Nibble #5 | Data Nibble #6 | # of Nibbles |
|---------------|-----------------------------|----------------------------|----------------------------|------------------------------|-----------------------------|-----------------------------|--------------|
| 0 | <code>mag_out [11:8]</code> | <code>mag_out [7:4]</code> | <code>mag_out [3:0]</code> | – | – | – | 3 |
| 1 | <code>mag_out [11:8]</code> | <code>mag_out [7:4]</code> | <code>mag_out [3:0]</code> | <code>diag [7:4]</code> | <code>diag [3:0]</code> | <code>count [3:0]</code> | 6 |
| 2 | <code>mag_out [11:8]</code> | <code>mag_out [7:4]</code> | <code>mag_out [3:0]</code> | <code>count [11:8]</code> | <code>count [7:4]</code> | <code>count [3:0]</code> | 6 |
| 3 | <code>mag_out [11:8]</code> | <code>mag_out [7:4]</code> | <code>mag_out [3:0]</code> | <code>temp_out [11:8]</code> | <code>temp_out [7:4]</code> | <code>temp_out [3:0]</code> | 6 |

CHECKSUM (CRC) NIBBLE

The CRC consists of 4 bits derived from the data nibbles only. The CRC is calculated using the polynomial $x^4 + x^3 + x^2 + 1$ with a seed of 4'b0101. For the shared SENT protocols, SSENT and ASENT, there is an option that SCN is included into the CRC

nibble (sen_crc_has_scn = 1, includes SCN into CRC).

OUTPUT DRIVER FALL TIME SELECTION

User is allowed to change the fall time of the output digital signal using the EEPROM parameter outdrv_sel. See Table 12 below.

Table 12: Code vs C_{LOAD} for outdrv_sel

| | | |
|-------------------------|--|---|
| Function | Output Signal Configuration Sets configuration of the output signal slew-rate control. Sets the ramp rate on the gate of the output driver, thereby changing slew rate at the output. | |
| Syntax | Field width: 3 bits | |
| Related Commands | - | |
| Values | Code | Fall Time (Typical), see Figure 14: Test Circuit (µs) |
| | | C _{LI} = 1.5 nF, C _{LX} = 0 |
| | 0 (Default) | 0.11 |
| | 1 | 0.18 |
| | 2 | 0.27 |
| | 3 | 0.35 |
| | 4 | 0.70 |
| | 5 | 1.24 |
| | 6 | 2.42 |
| | 7 | 3.55 |
| Options | - | |
| Examples | - | |




Figure 14: Fall Time Test Circuit

Table 13: Message Frame Section Definitions

| Section | Description |
|--|---|
| SYNCHRONIZATION AND CALIBRATION | |
| Function | Provide the external controller with a detectable start of the message frame. The large quantity of ticks distinguishes this section, for ease of distinction by the external controller. |
| Syntax | Nibbles: 1 Quantity of ticks: 56 Quantity of bits: 1 |
| STATUS AND COMMUNICATION | |
| Function | Provides the external controller with the status of the A1342 and indicates the format and contents of the Data section. |
| Syntax | Nibbles: 1 Quantity of ticks: 12 to 27 Quantity of bits: 4 1:0 Device status (see Table 20) 3:2 Message serial data protocol (sent_slow_ser_dis) |
| DATA | |
| Function | Provides the external controller with data selected by the sent_data_cfg parameter. |
| Syntax | Nibbles: 3 to 6 Quantity of ticks: 12 to 27 (each nibble) Quantity of bits: 4 (each nibble) |
| CRC | |
| Function | Provides the external controller with cyclic redundancy check (CRC) data for certain error detection routines applied to the Data nibbles and to the Status information. |
| Syntax | Nibbles: 1 Quantity of ticks: 12 to 27 (each nibble) Quantity of bits: 4 |
| PAUSE PULSE | |
| Function | Additional time can be added at the end of a SENT message frame to ensure all message frames are of appropriate length. |
| Syntax | Nibbles: NA Quantity of ticks: Quantity of bits: NA |
| TRIGGER PULSE | |
| Function | (Optional) Allow the external controller to determine when to transmit data |
| Syntax | Nibbles: NA Output must be held low a minimum of 1.8 μ s after the pause pulse. |

SAEJ2716 SENT AND TSENT

The A1342 SENT output is configurable for four (4) transmission modes, Internal Synchronous Mode, External Trigger Mode (TSENT), SSENT or ASENT. The transmission modes are configured by setting the parameter `outmsg_mode`.

When configured for Internal Synchronous Mode, `outmsg_mode = 1`, the SENT output transmits continuously, while in normal operating conditions. The SENT message frame rate is correlated to the internal update rate of the device (see Figure 16). The pause pulse is extended to correlate with the next available sample.

When configured for External Trigger Mode, `outmsg_mode = 2`, the SENT output transmits when requested by the external controller (see Figure 17). The pause pulse is extended until the next trigger pulse.

The external controller initiates a trigger pulse by holding the output pin low. The data sample is latched at the next internal update, 128 kHz, after the falling edge of the trigger pulse. The SENT frame is transmitted when external controller releases the output, the rising edge of the trigger pulse. After the rising edge of the trigger pulse the output remains high for minimum of seven SENT tick times before going low to initiate the start of the SENT synchronization pulse. For the fastest SENT rates, the start of the SENT synchronization pulse may be delayed longer than seven ticks to allow enough time for signal processing of the latched data. This is done to preserve a minimum time of 70.4 μs from the falling edge of the trigger pulse to end of the sync pulse, required for internal signal processing.




Figure 15: External BIST Request with Triggered SENT Output Mode




Figure 16: SENT Synchronization with Output Data and Internal Synchronous Mode




Figure 17: SENT Synchronization with Output Data and External Trigger Mode

Table 14: SENT Frame Rate

| PWM/SENT Code | ASSENT/SSENT | TSENT/SENT | PWM |
|---------------|--|--|--------------------------------------|
| | Tick Time (μs) ^[1] | Tick Time (μs) ^[1] | f_{PWM} (Hz) ^[2] |
| 0 | 0.12 | 3.05 | 125 |
| 1 | 0.12 | 3.05 | 167 |
| 2 | 0.24 | 3.05 | 250 |
| 3 | 0.37 | 3.05 | 333 |
| 4 | 0.49 | 14.77 | 500 |
| 5 | 0.61 | 9.64 | 667 |
| 6 | 0.73 | 7.32 | 800 |
| 7 | 0.85 | 6.10 | 1000 |
| 8 | 0.98 | 4.76 | 1333 |
| 9 | 1.10 | 3.54 | 1600 |
| 10 | 1.22 | 2.44 | 2000 |
| 11 | 1.34 | 1.71 | 2667 |
| 12 | 1.46 | 1.22 | 4000 |
| 13 | 1.59 | 0.85 | 5333 |
| 14 | 1.71 | 0.61 | 8000 |
| 15 | 1.83 | 0.61 | 16000 |
| 16 | 1.95 | – | – |
| 17 | 2.08 | – | – |
| 18 | 2.20 | – | – |
| 19 | 2.32 | – | – |
| 20 | 2.44 | – | – |
| 21 | 2.56 | – | – |
| 22 | 2.69 | – | – |
| 23 | 2.81 | – | – |
| 24 | 2.93 | – | – |
| 25 | 3.05 | – | – |
| 26 | 3.17 | – | – |
| 27 | 3.30 | – | – |
| 28 | 3.42 | – | – |
| 29 | 3.54 | – | – |
| 30 | 3.66 | – | – |
| 31 | 3.78 | – | – |

^[1] The combination of C_{L1} and output pull-up resistor may prevent use of some tick times due to increased output rise time.

^[2] f_{PWM} frequencies of 2000 Hz or greater may reduce output resolution.

SSENT ADDRESSING PROTOCOL

The SSENT protocol requires Sensors on the bus to be polled in sequential order, meaning increasing, consecutive, and rotating order by SensorID starting with SensorID 0. The Slot for a Sensor is the time at which that Sensor is expected to respond to an AddressingPulse and other Sensors are expected to not respond.

Each Sensor independently maintains a SlotCounter that is incremented each time the Sensor detects an AddressingPulse. This SlotCounter becomes the SlotNumber, which is used by the Sensor to decide which Sensor is being polled by the Host. The SlotCounter is compared to the SensorID, and if they match, that Sensor responds with the SENT Frame, and all other Sensors do not respond, although they increment their own SlotCounter. If the SlotCounter is incremented past the total number of Sensors on the bus (C_MAX_SENSOR option), the SlotCounter is returned to 0. Each Sensor must be programmed consistently with the total number of Sensors so they all roll over to 0 at the same count. Sensors do not increment their SlotCounter on a BroadcastPulse.

The SSENT protocol relies on each Sensor maintaining the exact same SlotNumber by counting the AddressingPulses. In order to synchronize all Sensors to the same SlotNumber, the SSENT protocol has a broadcast F_SYNC pulse that is used by the Host to force all Sensors to reset their SlotCounter to 0.

In order to reduce the burden on the Host, and also to improve detection and recovery from BusContention or system errors affecting the SENT bus, the SSENT protocol has the following configuration options that can be selected.

- C_SLOT_MARKING (cfg_slot_marking, 0x14). When enabled, each Sensor will wait a different length of time following an AddressingPulse, based on their SensorID. This leaves the SENT bus in a high state for a varying duration before the Sensor pulls the line low to begin the SENT Frame. All Sensors on the bus (including the addressed Sensor) measure this time to interpret the SensorID of the transmitting sensor. By comparing this to the SlotCounter, each Sensor can recognize if an unexpected Sensor responded to the AddressingPulse. By default, the Sensor would then drop Offline, since it cannot be known which Sensor is out of sync. This option increases the overhead on the bus and therefore reduces the maximum rate at which Sensors can be polled. SlotMarking increases the polling time of a Sensor by the SlotMarking time for that Sensor. All sensors on a bus must be configured with the same choice for this option.

Table 15: Slot Marking Delay Times for SSENT

| SensorID | Delay Time Ticks (Nominal) |
|----------|----------------------------|
| 0 | 7 |
| 1 | 18 |
| 2 | 36 |
| 3 | 62 |

Note:

It is not recommended using the slot marking option under a tick time of 1.2 μs since delay time associated with the Sensor ID might be too short for the sensor to process and give out the new sample.




Figure 18: SSENT Sensor Addressing




Figure 19: SSENT Sensor Addressing – No Slot Marking (3 Sensors on Bus)

- **C_SLOT_SYNC** (cfg_slot_sync, 0x14). When enabled in conjunction with **C_SLOT_MARKING**, a Sensor that is in BusSync for a reason other than BusContention will load its SlotCounter with the measured SlotNumber from the first AddressingPulse that does not have a Timeout. A Sensor would normally be Offline as a result of powering up, reset, or diagnostics. As long as any Sensor is Online and responding, this allows all other Sensors that are Offline to automatically synchronize their SlotCounter and begin responding correctly to future AddressingPulses targeting that Sensor. If all Sensors are offline, though, the Host must detect that no Sensor responds, and issue the **F_SYNC** function.
- **C_POR_OFFLINE** (cfg_por_offline, 0x14). When enabled, a Sensor will stay Offline until the Host issues **F_SYNC**, or one of the other synchronization options takes effect (**C_SLOT_SYNC** or **C_IDLE_SYNC**). If disabled, a Sensor will power-up with its SlotCounter set to 0, and will go directly Online. This allows the Sensors to initialize without any Host interaction. However, if a Sensor gets power-on-reset after the bus is in operation, its counter may be out of synch with other Sensors, and this could result in bus contention.
- **C_IDLE_SYNC** (cfg_slot_sync, 0x14). When enabled, a Sensor will monitor the bus for a long high (BusIdle) period greater than 510 ticks and reset its SlotCounter to 0. This option could be used if Sensor polling is expected to always be periodic and continuous, such that the only extended BusIdle time would be after power-up.

SSENT FUNCTION PULSES

SSENT has a set of function pulses where the host controller must hold the output low. The duration of the low pulse provided by the host controller defines the function, as described in Table 17 and Table 18. Following the low pulse, if the part is addressed to respond and the slot number matches the device slot counter, the device delays the output SENT frame with a minimum of 7 ticks high period to differentiate between the host trigger, and the device response. For the fast tick times, the 7 tick high period

may be extended, to preserve a minimum time of 70.4 μ s from the rising edge of the function pulse to the end of the sync pulse required for internal processing. Whether the device responds to a function pulse is defined by the purpose of each pulse.

- **F_OUTPUT**: Addressed sensor will return a SENT frame with sampled magnetic data. If there is data from a sample-and-hold operation available (**F_SAMPLE** or via **C_ZERO_SAMPLE=1** [cfg_zero_sample, 0x14]), then that data is returned, otherwise current data is sampled and returned. A Sensor configured with **C_ZERO_SAMPLE=1** will sample-and-hold on the rising edge of the **F_OUTPUT** pulse for Slot 0. A Sensor configured with **C_NO_SAMPLE=1** (cfg_no_sample, 0x14) and **C_ZERO_SAMPLE=0** will never sample-and-hold, so will always return current data in response to **F_OUTPUT**.
- **F_SAMPLE**: All sensors except those configured for **C_NO_SAMPLE=1** will sample and hold their data at the rising edge of the pulse. If **C_SAMPLE_ADR=0** (cfg_fsampl_ adr, 0x14), this is a BroadcastPulse to a Sensor, and that Sensor will not respond. If **C_SAMPLE_ADR=1**, this is also an AddressingPulse to a Sensor, and the addressed sensor will return a SENT frame with either the sampled or current data. It is recommended, but not required, that all Sensors on the bus be configured the same.
- **F_DIAG**: Sensor(s) will enter self-test Diagnostics based on **C_DIAG_ENABLE** (lbist_dis, 0x9) and **C_DIAG_ADR** (cfg_diag_ adr, 0x14) options. If configured with **C_DIAG_ADR=0**, the Sensor treats **F_DIAG** as a BroadcastPulse, does not respond, and immediately enters Diagnostics unless **C_DIAG_ENABLE=0**. If configured with **C_DIAG_ADR=1**, the Sensor treats **F_DIAG** as an AddressingPulse. The addressed Sensor does not respond, but enters diagnostics if **C_DIAG_ENABLE=1**.
- **F_SYNC**: All Sensors will synchronize their SlotNumbers by setting their SlotCounters such that the next AddressingPulse is for Slot 0.




Figure 20: SSENT Sensor Addressing - with Slot Marking (4 Sensors on Bus)

Table 16: SSENT Function Pulses in short_trigger Mode, outmsg_mode = 4

| Function | Type | Min. Tick | Nom. Tick | Max. Tick |
|----------|----------------------|-----------|-----------|-----------|
| F_OUTPUT | Addressing/Broadcast | 15 | 17 | 19 |
| F_SAMPLE | Addressing/Broadcast | 31 | 35 | 39 |
| F_DIAG | Addressing/Broadcast | 56 | 63 | 70 |
| F_SYNC | Broadcast | 93 | 104 | 115 |

Table 17: SSENT Function Pulses in long_trigger Mode, outmsg_mode = 3

| Function | Type | Min. Tick | Nom. Tick | Max. Tick |
|----------|----------------------|-----------|-----------|-----------|
| F_OUTPUT | Addressing/Broadcast | 9 | – | 81 |
| F_SYNC | Broadcast | 105 | 140 | 171 |
| F_DIAG | Addressing/Broadcast | 216 | 240 | 264 |

ASENT ADDRESSING PROTOCOL

The ASENT protocol allows Sensors to be polled in an arbitrary order. The SensorID is transmitted by the Host following any AddressingPulse as a series of 0, 1, 2, or 3 IncAdrPulses. After this sequence, the SENT line is left in a high state, and each sensor will recognize after a time period of about 18 nominal ticks

that there are no more IncAdrPulses coming. This 18 tick high period may be delayed to allow enough time for signal processing of the latched data. This is done to preserve a minimum time of 70.4 μs from the rising edge of the function and addressing pulse to end of the sync pulse, required for internal signal processing. The sensor whose ID matches the number of IncAdrPulses received will respond.




Figure 21: ASENT IncAdrPulse (output by Host)




Figure 22: ASENT Sensor Addressing

ASENT FUNCTION PULSES

- **F_OUTPUT:** Addressed sensor will return a SENT frame with sampled magnetic data. If there is data available from a sample-and-hold operation (F_SAMPLE), then that data is returned, otherwise current data is sampled and returned. A Sensor configured with C_NO_SAMPLE=1 will not sample-and-hold, so will always return current data in response to F_OUTPUT.
- **F_SAMPLE:** All sensors except those configured for C_NO_SAMPLE=1 will sample and hold their data at the rising edge of the pulse. If C_SAMPLE_ADR=0, this is a BroadcastPulse to a Sensor, and that Sensor will not respond. If C_SAMPLE_ADR=1, this is also an AddressingPulse to a Sensor, and the addressed sensor will return a SENT frame with either the sampled or current data. It is recommended, but not required, that all Sensors on the bus be configured the same.
- **F_DIAG:** Sensor(s) will enter self-test Diagnostics based on C_DIAG_ENABLE and C_DIAG_ADR options. If configured with C_DIAG_ADR=0, the Sensor treats F_DIAG as a BroadcastPulse, does not respond, and immediately enters Diagnostics unless C_DIAG_ENABLE=0. If configured with C_DIAG_ADR=1, the Sensor treats F_DIAG as an AddressingPulse. The addressed Sensor does not respond, but enters diagnostics if C_DIAG_ENABLE=1.

Serial Communication

The serial interface allows an external controller to read and write registers, including EEPROM, in the A1342 using a point-to-point command/acknowledge protocol. The A1342 does not initiate communication; it only responds to commands from the external controller. Each transaction consists of a command from the controller. If the command is a write, there is no acknowledging from the A1342. If the command is a read, the A1342 responds by transmitting the requested data.

NOTE:

It is the external controller's responsibility to avoid sending a Command Frame which overlaps a Read Acknowledge frame.

The serial interface uses a Manchester encoding based protocol per G.E. Thomas (0 = rising edge, 1 = falling edge), with address and data transmitted MSB first. Four commands are recognized by the A1342: Write Access Code, Write to Volatile Memory, Write to Non-Volatile Memory (EEPROM) and Read. One frame type, Read Acknowledge, is sent by the A1342 in response to a Read command.

Table 18: ASENT Function Pulses

| Function | Type | Min. Tick | Nom. Tick | Max. Tick |
|----------|----------------------|-----------|-----------|-----------|
| F_OUTPUT | Addressing/Broadcast | 15 | 17 | 19 |
| F_SAMPLE | Addressing/Broadcast | 31 | 35 | 39 |
| F_DIAG | Addressing/Broadcast | 56 | 63 | 70 |




Figure 23: Top-Level Programming Interface

PROGRAMMING INFORMATION

The A1342 device uses a three-wire programming interface, where the input signal on VCC controls the program enable signal, data is transmitted on VOUT, and all signals are referenced to ground. This three-wire interface make it possible to use multiple devices with shared VCC and ground lines.

Four transactions, write access, write to EEPROM, write to volatile memory, and read, are shown in the Figure 24 to Figure 28. To initialize any communication, V_{CC} increases to a level above V_{PRGH}(min). At this time, VOUT is disabled and acts as input. After program enable is asserted, the external controller

must drive the output low for a minimum of two Manchester bit periods before sending the message frame. Once the command is complete, V_{CC} is reduced below V_{PRGL}(max) back to its normal operating level, the output is enabled and responds to magnetic input.

When performing a write to EEPROM transaction, the A1342 requires a delay of t_w to store the data into the EEPROM. The device will respond with a high-to-low transition on VOUT to indicate the write to EEPROM sequence is complete.

Table 19: Programming Characteristics

| Parameter | Symbol | Description | Min. | Typ. | Max. | Unit |
|-------------------------------|---------------------|--|------------------------------|------|-----------------------------|---------------------------------|
| Program Enable Voltage (High) | V _{PRGH} | dev_lock = 0, 1, 2, 4, 7 | V _{CC(OV)HIGH(max)} | – | 19 | V |
| | | dev_lock = 3 | V _{CC(HV)HIGH(max)} | – | 19 | V |
| Program Enable Voltage (Low) | V _{PRGL} | dev_lock = 0, 1, 2, 4, 7 | – | – | V _{CC(OV)LOW(min)} | V |
| | | dev_lock = 3 | – | – | V _{CC(HV)LOW(min)} | V |
| Manchester Start Delay | t _m | Minimum delay before first edge of the Manchester signal. | 200 | – | – | μs |
| Output Enable Delay | t _e | | – | 25 | – | μs |
| Program Time Delay | t _d | | – | – | 50 | μs |
| Program Write Delay | t _w | | – | 20 | – | ms |
| Bit Time Delay | t _b | | – | 2 | – | t _{bit} ^[1] |
| BIST Output Enable | t _i | Time for V _{CC} to reduce below V _{PRGL} for BIST acknowledgment | – | – | 2 | ms |
| Access Code Timeout | t _{acc} | | 500 | – | – | ms |
| Bit Rate | | Communication Rate | 4 | – | 100 | kBPS |
| Manchester High Voltage | V _{MAN(H)} | Data pulses on VOUT | 2.8 | – | V _{CC} | V |
| Manchester Low Voltage | V _{MAN(L)} | Data pulses on VOUT | 0 | – | 1.2 | V |

^[1] The unit t_{bit} is the period for single bit defined by the Manchester encoding bit boundaries and is determined by the communication rate.




Figure 24: Write Access Code




Figure 25: Write to Volatile Memory




Figure 26: Write to Non-Volatile Memory (EEPROM)




Figure 27: Read Request




Figure 28: BIST Request

Read and Write Transmission

The A1342 has an advanced read and write message format that permits reading and writing a partial bits of a selected address. The addresses are split into two bit fields; field 1 contains bits [11:0], field 2 contains bits [25:12]. The field select bits in the message frame determine how an address is accessed. For a description, see Figure 30.

CRC

The serial interface uses a cyclic redundancy check (CRC) for data-bit error checking (synchronization bits are ignored during the check). The CRC algorithm is based on the following polynomial, and the calculation is represented graphically in Figure 31.

$$g(x) = x^3 + x + 1$$

The trailing 3 bits of a message frame comprise the CRC token. The CRC is initialized at 111 (see Figure 31).

| | | | | | | | | | | | | |
|-------|-----------------------------------|-----|----------------------|----|-----|----|----------------------|---------------------|----|-----|-----------------|--------------|
| Field | 31 | --- | 26 | 25 | --- | 14 | 13 | 12 | 11 | --- | 0 | Data Bit |
| F=0 | Write = DC Read = ECC | | Field 2 data [25:12] | | | | Field 1 data [11:0] | | | | Entire Register | |
| F=1 | Write = don't care (DC), Read = 0 | | | | | | | Field 1 data [11:0] | | | | Field 1 only |
| F=2 | Write = don't care (DC), Read = 0 | | | | | | Field 2 data [25:12] | | | | Field 2 only | |

Figure 30: Read Acknowledge or Write Frame General Structure




Figure 31: CRC Calculation

Customer/Factory Access Modes

The internal memory is accessible via the serial interface. The memory address space is divided into two areas: Factory and Customer.

Access is controlled by a specific code, which must be loaded within 500 milliseconds of power-on. The access codes are constants. The customer access code is given in Table 21.

For software convenience, the table gives an 8 bit “address” and 32 bit “data” field, similar to a normal Write command format (the address and data fields concatenated yield the full access code). The Customer area can be written only if the serial interface receives a Customer Unlock code within 500 milliseconds after power-on reset. When the customer access code is received, factory registers are addressable but are read only.

Table 21: Customer Access Code

| Name | Serial Interface Format | |
|----------|-------------------------|------------|
| | Address (Hex) | Data (Hex) |
| Customer | 0x79 | 0xC41D3432 |

Customer Memory Lock

The A1342 contains lock features to prevent access to the device memory. The EEPROM parameter, dev_lock bits [2:0] in register cfg_c, configure the lock mode. When dev_lock is set to 0, 1, 2, 4, or 7, full read and write access to the EEPROM is enabled. When dev_lock is set to 3, write access to the EEPROM is disabled, write access to the volatile memory is enabled, and read access to the entire memory is enabled. When dev_lock is set to 6, write access to the device is disabled and read access to the entire memory is enabled. When dev_lock is set to 5, all write and read access to the device is disabled.

Note:

Setting dev_lock to 5 may limit some factory debug support.

EEPROM Margin Checking

The A1342 contains a test mode, called EEPROM Margining, to check the logic levels of the EEPROM bits. EEPROM margining is accessible with customer EEPROM access. EEPROM margining is selectable to check all logic 1 bits, logic 0 bits, or both. To run EEPROM Margining—checking both logic 1 and logic 0 bits for the entire EEPROM—write the parameter margin_start in address marg_tst_c, 0x43, to logic 1. The results of the test are reported back in EEPROM registers ee_data_c, 0x41, and ee_status_c, 0x42. For more EEPROM Margining information and options, refer to the table Memory Address Map.

Note:

A fail of the margin test does not force the output to a diagnostic state.

MEMORY ADDRESS MAP

Table 22: Memory Address Map

| Type ⁽¹⁾ | Group | Register Name | Addr | Field Name | Description | Access | Size | MSB | LSB | |
|--|---------|---------------|-----------|---|--|--------|------|-----|-----|----|
| eeprom (continued on the next page) | id_cfg | wlot_f | 0x00 | factory_lot | Factory Lot Number | ro | 16 | 15 | 0 | |
| | | | | factory_wafer | Factory Wafer Number | ro | 6 | 21 | 16 | |
| | | | | unused | | ro | 4 | 25 | 22 | |
| | | id_f | 0x01 | x_die_loc | 8-bit X die location | ro | 8 | 7 | 0 | |
| | | | | y_die_loc | 8-bit Y die location | ro | 8 | 15 | 8 | |
| | | | | unused | | ro | 10 | 25 | 16 | |
| | | id_c | 0x02 | cust_id | Bits reserved for customer ID | rw | 22 | 21 | 0 | |
| | | | | die_addr_0 | Die address for Manchester communication and Shared SENT | rw | 1 | | 22 | |
| | | | | die_addr_1 | Die address for Manchester communication and Shared SENT | rw | 1 | | 23 | |
| | unused | | | | rw | 2 | 25 | 24 | | |
| | sens_c | sens_trim_c | 0x03 | sens_c | Customer Sensitivity trim (fine) | rw | 11 | 10 | 0 | |
| | | | | unused | | rw | 1 | | 11 | |
| | | | | sensm_c | Customer Sensitivity trim (coarse) multiplier: 0: 1× 1: 2× 2: 4× 3: 8× 4: 16× 5: 32× 6: 32× 7: 32× | rw | 3 | 14 | 12 | |
| | | | | pol_c | Magnetic sensitivity polarity (0 = + south pole, 1 = - south pole) | rw | 1 | | 15 | |
| | | | | bw_sel_c | Bandwidth selection for signal path IIR filter: 0: 40 Hz 1: 160 Hz 2: 680 Hz 3: 3000 Hz 4-7: 7400 Hz | rw | 3 | 18 | 16 | |
| | | | | bw_sel_comp_c | Reference coil path bandwidth selection for IIR Filter: 0: 0.08 Hz 1: 0.3 Hz 2: 1.25 Hz 3: 4 Hz 4-7: 16 Hz | rw | 3 | 21 | 19 | |
| | | sensctc1_c | 0x04 | ee_spare_c | Spare control in customer space. Brought to top level outputs. | rw | 4 | 25 | 22 | |
| | | | | senstc1_hot_c | 1st order customer sensitivity temperature compensation, room to hot | rw | 11 | 10 | 0 | |
| | | | | unused | | rw | 1 | | 11 | |
| | | | | senstc1_cld_c | 1st order customer sensitivity temperature compensation, room to cold | rw | 11 | 22 | 12 | |
| | | sensctc2_c | 0x05 | unused1 | | rw | 3 | 25 | 23 | |
| | | | | senstc2_hot_c | 2nd order customer sensitivity temperature compensation, room to hot | rw | 10 | 9 | 0 | |
| | | | | unused | | rw | 2 | 11 | 10 | |
| | | | | senstc2_cld_c | 2nd order customer sensitivity temperature compensation, room to cold | rw | 10 | 21 | 12 | |
| | | qout_c | qo_trim_c | 0x06 | unused1 | | rw | 4 | 25 | 22 |
| | qo_c | | | | Customer Quiescent Output (QO) adjustment (fine) | rw | 16 | 15 | 0 | |
| | qotc_c | | 0x07 | qotc_hot_c | 1st order QO temperature compensation, room to hot | rw | 12 | 11 | 0 | |
| | | | | qotc_cld_c | 1st order QO temperature compensation, room to cold | rw | 12 | 23 | 12 | |
| | clamp_c | 0x08 | unused | | rw | 2 | 25 | 24 | | |
| | | | clamph | High Clamp: 0x000 = upper rail, 0xFFFF = clamp(min) | rw | 12 | 11 | 0 | | |
| | | | clampl | Low Clamp: 0x000 = lower rail, 0xFFFF = clamp(max) | rw | 12 | 23 | 12 | | |
| | | | | | unused | | rw | 2 | 25 | 24 |

Continued on the next page...

Table 22: Memory Address Map (continued)

| Type [1] | Group | Register Name | Addr | Field Name | Description | Access | Size | MSB | LSB | |
|--------------------|-----------------------------------|---------------|--|------------|--|-----------------------------|------|-----|-----|----|
| eeprom (continued) | cfg_c | 0x09 | dev_lock | | 0 - Write and read access permitted. 1 - Write and read access permitted. 2 - Write and read access permitted. 3 - EEPROM Lock: Prevents writes to EEPROM but all registers including shadow can be written. All registers and EEPROM can be read. 4 - Write and read access permitted. 5 - Full Lock: Prevents all access to the device. 6 - Write Lock: Prevents writing anything to either EEPROM or registers. All registers and EEPROM can still be read. 7 - Write and read access permitted. | rw | 3 | 2 | 0 | |
| | | | unused1 | | | rw | 7 | 9 | 3 | |
| | | | cfg_spcmin_adj | | Determines minimum low time for detecting an SSENT, Long Trigger Mode, F_OUTPUT command. 0: 7 ticks 1: 8 ticks 2: 9 ticks 3: 10 ticks | rw | 2 | 11 | 10 | |
| | | | out_msg_imm | | 0: Waits after a power-on reset for some time to allow signal path to settle before sending first PWM or SENT message 1: Do not wait for signal path to settle before sending first PWM or SENT message | rw | 1 | | 12 | |
| | | | coil_freq | | Fraction of time coil is turned on. When coil is off, triggered CoilBIST can be invoked with a BIST request. 0: Coil always on 1: 1/2 time 2: 1/256 time 3: Coil always off. CoilBIST acknowledge is available following BIST. | rw | 2 | 14 | 13 | |
| | | | report_dig_err | | Has no function. | rw | 1 | | 15 | |
| | | | coilcomp_dis | | 0: Coil compensation remains enabled 1: Disables coil compensation | rw | 1 | | 16 | |
| | | | diag_mode | | 0: Default outputs a diag message in PWM / SENT 1: Outputs is high Z for all diagnostic errors. Only supported when V _{OUT} is configured for PWM, outmsg_mode = 0. | rw | 1 | | 17 | |
| | | | lbist_dis | | 0: BIST check enabled following a BIST request. 1: Prevent BIST check from responding to a BIST request | rw | 1 | | 18 | |
| | | | coilbist_dis | | 0: Coil measurement monitor will report errors 1: Prevent coil measurement monitor from reporting errors at the output | rw | 1 | | 19 | |
| | | | uvd_dis | | 0: Undervoltage errors will be reported 1: Prevent undervoltage detection from reporting errors at the output | rw | 1 | | 20 | |
| | | | ovd_dis | | 0: Overvoltage errors will be reported 1: Prevent overvoltage detection from reporting errors at the output | rw | 1 | | 21 | |
| | | | otmp_dis | | 0: Overtemperature errors will be reported 1: Prevent overtemperature monitor from reporting errors at the output | rw | 1 | | 22 | |
| | | | oor_dis | | 0: Magnetic signal out-of-range errors will be reported 1: Prevent out-of-range monitor from reporting errors at the output | rw | 1 | | 23 | |
| | | | lbist_ack | | Determines if a Logic BIST acknowledge message (SENT or PWM) should be transmitted following BIST 0: Do not send a message 1: Send a message | rw | 1 | | 24 | |
| | coilbist_ack | | Determines if a CoilBIST acknowledge message (SENT or PWM) should be transmitted following BIST 0: Do not send a message 1: Send a message | rw | 1 | | 25 | | | |
| | lin_c (continued on next page) | lin0_c | 0x0A | lint00 | | Linearization Table entry 0 | rw | 12 | 11 | 0 |
| | | | | lint01 | | Linearization Table entry 1 | rw | 12 | 23 | 12 |
| | | | | unused | | | rw | 2 | 25 | 24 |
| | | lin1_c | 0x0B | lint02 | | Linearization Table entry 2 | rw | 12 | 11 | 0 |
| | | | | lint03 | | Linearization Table entry 3 | rw | 12 | 23 | 12 |
| | | | | unused | | | rw | 2 | 25 | 24 |
| | | lin2_c | 0x0C | lint04 | | Linearization Table entry 4 | rw | 12 | 11 | 0 |
| | | | | lint05 | | Linearization Table entry 5 | rw | 12 | 23 | 12 |
| | | | | unused | | | rw | 2 | 25 | 24 |

Continued on the next page...

Table 22: Memory Address Map (continued)

| Type [1] | Group | Register Name | Addr | Field Name | Description | Access | Size | MSB | LSB |
|--------------------|--|---------------------------------------|---------------------------|---------------|--|--------|------|-----|-----|
| eeprom (continued) | lin_c | lin3_c | 0x0D | lint06 | Linearization Table entry 6 | rw | 12 | 11 | 0 |
| | | | | lint07 | Linearization Table entry 7 | rw | 12 | 23 | 12 |
| | | | | unused | | rw | 2 | 25 | 24 |
| | | lin4_c | 0x0E | lint08 | Linearization Table entry 8 | rw | 12 | 11 | 0 |
| | | | | lint09 | Linearization Table entry 9 | rw | 12 | 23 | 12 |
| | | | | unused | | rw | 2 | 25 | 24 |
| | | lin5_c | 0x0F | lint10 | Linearization Table entry 10 | rw | 12 | 11 | 0 |
| | | | | lint11 | Linearization Table entry 11 | rw | 12 | 23 | 12 |
| | | | | unused | | rw | 2 | 25 | 24 |
| | | lin6_c | 0x10 | lint12 | Linearization Table entry 12 | rw | 12 | 11 | 0 |
| | | | | lint13 | Linearization Table entry 13 | rw | 12 | 23 | 12 |
| | | | | unused | | rw | 2 | 25 | 24 |
| | | lin7_c | 0x11 | lint14 | Linearization Table entry 14 | rw | 12 | 11 | 0 |
| | | | | lint15 | Linearization Table entry 15 | rw | 12 | 23 | 12 |
| | | | | unused | | rw | 2 | 25 | 24 |
| | | lin8_c | 0x12 | lint16 | Linearization Table entry 15 | rw | 12 | 11 | 0 |
| | | | | lint_e | 0: Bypass linearization table 1: Enable valid linearization table | rw | 1 | | 12 |
| | | | | lint_bin_e | 0: Linearization mode functions normally if enabled by lint_e 1: Enable bin mode for linearization table | rw | 1 | | 13 |
| | | | | lint_out_inv | 0: Normal output of linearization table 1: Invert output of linearization table | rw | 1 | | 14 |
| | | | | lint_in_inv | 0: Normal input to linearization table 1: Invert input of linearization table | rw | 1 | | 15 |
| | | | | unused | | rw | 10 | 25 | 16 |
| | | post_lin_c | 0x13 | plin_sens | Post Linearization sensitivity adjustment | rw | 12 | 11 | 0 |
| | | | | plin_qvo | Post Linearization offset adjustment | rw | 12 | 23 | 12 |
| | | | | unused | | rw | 2 | 25 | 24 |
| | | out_cfg_c (continued on next page) | 0x14 (cont. next page) | outmsg_mode | 0: PWM 1: SENT 2: TSENT 3: SSENT, Long Trigger Mode 4: SSENT, Short Trigger Mode 5-7: ASENT | rw | 3 | 2 | 0 |
| | | | | sent_pwm_rate | Specifies the frequency of the SENT or PWM message. This is shown in Table 14. | rw | 5 | 7 | 3 |
| | | | | sent_data_cfg | Only valid for SENT modes. Number and format of data nibbles in SENT frame. 0: 3 Data Nibbles 1: 6 Nibbles- 3 Magnetic Data Nibbles, 2 Diagnostic Flag Nibbles, 1 Counter Nibble 2: 6 Nibbles- 3 Magnetic Data Nibbles, 3 Counter Nibbles 3: 6 Nibbles- 3 Magnetic Data Nibbles, 3 Temperature Sensor Output Nibbles | rw | 2 | 9 | 8 |
| sent_slow_ser_dis | Selects bits for SCN[3:2]. Only valid for SENT mode. 0: Enables the slow serial message stream. 1: Disables the slow serial message stream. SCN bits are determined by sen_no_smsg | | | rw | 1 | | 10 | | |
| outdrv_sel | Adjust fall time of digital output. This is shown in Table 12. | | | rw | 3 | 13 | 11 | | |
| sen_crc_has_scn | Determines if SCN is included in CRC 0: SCN not included in CRC 1: SCN included in CRC | | | rw | 1 | | 14 | | |
| sen_no_smsg | Selects bits for SCN[3:2]. Only valid for SENT mode. Only valid if sent_slow_ser_dis = 1 0: SCN[3:2] = All Zeros 1: SCN[3:2] = Device ID. | | | rw | 1 | | 15 | | |

Continued on the next page...

Table 22: Memory Address Map (continued)

| Type ^[1] | Group | Register Name | Addr | Field Name | Description | Access | Size | MSB | LSB |
|---------------------------------------|-------------|-----------------------|---------------|---|--|--------|------|-----|-----|
| eeprom (continued) | | out_cfg_c (continued) | 0x14 (cont.) | cfg_max_sensor | Highest sensor number on the bus for SSENT | rw | 2 | 17 | 16 |
| | | | | cfg_diag_adr | Sets whether the diagnostic trigger is for a specific addressed sensor, or broadcast to all sensors 0: Diagnostic Trigger is broadcast mode (all sensors) 1: Diagnostic trigger is addressing mode (only addressed sensor) | rw | 1 | | 18 |
| | | | | cfg_no_sample | 0: F_SAMPLE will cause the sensor to sample and hold magnetic data 1: F_SAMPLE will not create a sample and hold of the magnetic data | rw | 1 | | 19 |
| | | | | cfg_fsampl_adr | 0: F_SAMPLE will not address the sensor 1: F_SAMPLE will be an addressing (frame request) as well as a sample and hold request | rw | 1 | | 20 |
| | | | | cfg_idle_sync | 0: A bus idle will not resynchronize the sensors 1: For SSENT Short or Long, a bus idle time of > 510 ticks will act as an F_SYNC pulse | rw | 1 | | 21 |
| | | | | cfg_por_offline | 0: The sensor will come online after a power-on reset 1: the sensor will be in OFFLINE mode following a power-on reset (but not a reset that is not also power-on) and will require an F_SYNC pulse to come online | rw | 1 | | 22 |
| | | | | cfg_slot_marking | 0: SSENT will not include slot marking times 1: for SSENT, the slot marking times will be applied prior to the start of a frame NOTE: This option is not recommended for tick times below 1.22 μs | rw | 1 | | 23 |
| | | | | cfg_slot_sync | 0: Slot marking will not resynchronize the slot counter 1: for SSENT and cfg_slot_marking=1, then the sequencer will use the slot marking to synchronize the slot counter | rw | 1 | | 24 |
| | | | | cfg_zero_sample | 0: A sample and hold will only be requested using an F_SAMPLE pulse 1: For SSENT, a sample_and_hold will be requested when the slot counter is 0 | rw | 1 | | 25 |
| | | Reserved | 0x15-0x1F | | Address 0x15 through 0x1F reserved for factory use | ro | | | |
| shadow | | | 0x22-0x3F | | Addresses 0x22 through 0x3F are reserved for shadow memory, a volatile representation of EEPROM. 0x22 is shadow from 0x02. | | | | |
| volatile (continued on the next page) | | test_c | 0x40 | out_dis | 0: No effect 1: test mode to disable output | rw | 1 | | 0 |
| | | | | ee_test_adr | If ee_use_test_adr is set, then margining or check testing will start at this address. If the test fails, this will contain the failing address | rw | 5 | 19 | 15 |
| | | | | ee_use_test_adr | 0: No effect 1: Uses ee_test_adr as the start address for margining. If ee_loop is set, this bit is ignored and the starting address is always 0x0 | rw | 1 | | 20 |
| | | | | ee_loop | 0: Test completes at final address or fail 1: Test loops until MARGIN_START is written low or fail | rw | 1 | | 21 |
| | | | | comm_en | Allows for serial communication without raising VCC 0: Default mode. VCC must be raised to allow serial communication 1: Serial communication can occur with VCC at nominal operating level | rw | 1 | | 22 |
| | | ee_data_c | 0x41 | ee_data | If margin or self test fails this is the failed data read from EEPROM. | rw | 26 | 25 | 0 |
| | ee_status_c | 0x42 | ee_dbe_flag | Latched and held high when a dbe has occurred. | rw | 1 | | 0 | |
| | | | ee_sbe_flag | Latched and held high when a sbe has occurred. | rw | 1 | | 1 | |
| | | | ee_err | Indicates an EEPROM write error occurred. This bit is latch and hold with clear on read. | rc | 1 | | 2 | |
| | | | ee_err_status | When ee_err is asserted this parameter contains a factory error code for the aborted EEPROM write transaction | ro | 5 | 7 | 3 | |
| | | | ee_addr | Reflects the read/write address to the EEPROM. This allows for a manual write to the EEPROM or will contain data read from the EEPROM if margining or self check fails. | rw | 5 | 12 | 8 | |
| | | | ee_ecc | Reflects bits [29:24] to be written to the eeprom or read from the eeprom. This allows for a manual write to the EEPROM or will contain data read from the EEPROM if margining or self check fails. | rw | 6 | 18 | 13 | |
| | | cp_err | | High to indicate an error occurred during charge pump ramp. ee_err_status stores information about the error. | rc | 1 | | 19 | |

Continued on the next page...

Table 22: Memory Address Map (continued)

| Type ^[1] | Group | Register Name | Addr | Field Name | Description | Access | Size | MSB | LSB |
|----------------------|--------------|---------------|---------------------|------------|---|--------|------|-----|-----|
| volatile (continued) | marg_lst_c | 0x43 | margin_min_max_fail | | If margining fails, this bit indicates if the min or max reference failed. 0: Min margining failed. 1: Max margining failed. | ro | 1 | | 5 |
| | | | margin_status | | Bits are cleared after a read or reset. 0: Reset condition (no result from margin testing) 1: Pass, no failure detected during margin testing 2: Fail, failure detected during margin testing 3: Running, margin test is still running | ro | 2 | 4 | 3 |
| | | | margin_no_min | | Does not perform minimum margin testing 0: Margining done a min voltage. 1: No margining at min voltage | rw | 1 | | 2 |
| | | | margin_no_max | | Does not perform maximum margin testing 0: Margining done a max voltage. 1: No margining at max voltage. | rw | 1 | | 1 |
| | | | margin_start | | Write to 1 to start margin testing. If EE_LOOP is low, this bit will self clear when address 0x1F is reached. If EE_LOOP is high, this bit must be written to 0 to stop test. This bit always clears on a fail. | rw | 1 | | 0 |
| | status_c | 0x44 | cust_access | | Indicates customer access enabled | ro | 1 | | 25 |
| | err_status_c | 0x45 | diag_reg_c | | Status bits to report diagnostic errors. 0 = no errors Bit [0] = 1: EEPROM Dual Bit Error Bit [1] = 1: Logic BIST Error Bit [2] = 1: CoilBIST error Bit [3] = 1: Undervoltage Error Bit [4] = 1: Overvoltage Error Bit [5] = 1: Overtemperature Error Bit [6] = 1: Signal Out of Range Low Error Bit [7] = 1: Signal Out of Range High Error | rw | 8 | 23 | 16 |
| | lbist_ctrl_c | 0x46 | run_lbist | | Runs BIST and may send result via SENT/PWM depending on customer configuration settings. | wo | 1 | | 0 |
| | | | lbist_sig | | LBIST Ack: 0x8A0 (Bit [7] = lbist pass [6:0] = lbist crc) | ro | 8 | 11 | 4 |
| | | | abist_sig | | ABIST Ack: [9:0] = CoilBIST acknowledge value. Passing values between 0x333 to 0xCD (2's complement). | ro | 10 | 21 | 12 |
| | sigpath_c | 0x47 | byp_trim_c | | 0: No effect 1: Bypass Customer Sensitivity and Offset trim | rw | 1 | | 0 |
| | | | byp_tc_c | | 0: No effect 1: Bypass Customer sensitivity and offset temp. compensation | rw | 1 | | 1 |
| | | | byp_lint | | 0: No effect 1: Bypass Linearization block | rw | 1 | | 2 |
| | | | byp_plin | | 0: No effect 1: Bypass Post-Linearization Trim block | rw | 1 | | 3 |
| | | | byp_clamp | | 0: No effect 1: Bypass Clamp block | rw | 1 | | 4 |
| | temp_out_c | 0x48 | temp_out | | Output of Temp Sensor Trim block | ro | 12 | 11 | 0 |
| | mag_out_c | 0x49 | mag_out | | Output of the magnetic signal path | ro | 12 | 11 | 0 |
| | | Reserved | 0x4A-0x59 | | Addresses 0x4A through 0x59 reserved for factory use | | | | |

^[1] All EEPROM addresses contain 32 bits. Bits 26 through 31 are used for EEPROM diagnostics. For more information, see Application Information: EEPROM Diagnostics.

PROGRAMMABLE PARAMETER REFERENCE

Table 23: die_addr_0: Address 0x02, field 2, bit 22
die_addr_1: Address 0x02, field 2, bit 23

| Function | Sets address of the die for SENT and Addressable Manchester | | | | | | | | | | | | | | | | | |
|------------------|---|----------------|--|------------|------------|----------------|---|---|---|---|---|---|---|---|---|---|---|---|
| Syntax | Quantity of bits 2 (1 for each parameter) | | | | | | | | | | | | | | | | | |
| Related Commands | outmsg_mode | | | | | | | | | | | | | | | | | |
| Values | <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th>die_addr_1</th> <th>die_addr_0</th> <th>Device Address</th> </tr> </thead> <tbody> <tr> <td>0</td> <td>0</td> <td>0</td> </tr> <tr> <td>0</td> <td>1</td> <td>1</td> </tr> <tr> <td>1</td> <td>0</td> <td>2</td> </tr> <tr> <td>1</td> <td>1</td> <td>3</td> </tr> </tbody> </table> | | | die_addr_1 | die_addr_0 | Device Address | 0 | 0 | 0 | 0 | 1 | 1 | 1 | 0 | 2 | 1 | 1 | 3 |
| die_addr_1 | die_addr_0 | Device Address | | | | | | | | | | | | | | | | |
| 0 | 0 | 0 | | | | | | | | | | | | | | | | |
| 0 | 1 | 1 | | | | | | | | | | | | | | | | |
| 1 | 0 | 2 | | | | | | | | | | | | | | | | |
| 1 | 1 | 3 | | | | | | | | | | | | | | | | |
| Options | | | | | | | | | | | | | | | | | | |

Table 24: : bw_sel_comp_c: Address 0x03, field 2, bits 21:19

| | |
|------------------|---|
| Function | Sets the 3 dB frequency of the calibration path filter for noise reduction. This setting has no effect on CoilBIST response time. |
| Syntax | Quantity of bits 3 |
| Related Commands | |
| Values | Code: 3 dB (Hz) 0: 0.08 Hz, 1: 0.3 Hz, 2: 1.25 Hz, 3: 4 Hz, 4-7: 16 Hz |
| Options | |

Table 25: bw_sel_c: Address 0x03, field 2, bits 18:16

| | |
|------------------|---|
| Function | Sets the 3 dB frequency for input magnetic signal path noise reduction |
| Syntax | Quantity of bits: 3 |
| Related Commands | |
| Values | Code: 3 dB (Hz) 0: 40 Hz, 1: 160 Hz, 2: 680 Hz, 3: 3000 Hz, 4-7: 7400 Hz Note: Decreasing the calibration path filter bandwidth may decrease the noise, while increasing the signal path compensation settling. |
| Options | |

Table 26: clamph: Address 0x08, field 1, bits 11:0

| | |
|------------------|---|
| Function | Sets level for the upper output clamp |
| Syntax | Quantity of bits: 12 Inverted, unsigned |
| Related Commands | clampl |
| Values | 0x0: Default, Upper output clamp is at $OUT_{CLP(HIGH)}(max)$ 0xFFF: Upper output clamp is at $OUT_{CLP(HIGH)}(min)$ |
| Options | |

Table 27: clampl: Address 0x08, field 2, bits 23:12

| | |
|------------------|---|
| Function | Sets level for the lower output clamp |
| Syntax | Quantity of bits: 12 |
| | unsigned |
| Related Commands | clamph |
| Values | 0x0: Default, lower output clamp is at $OUT_{CLP(LOW)(min)}$ 0xFFF: Upper output clamp is at $OUT_{CLP(LOW)(max)}$ |
| Options | |
| Examples | |

Table 28: sent_pwm_rate: Address 0x14, field 1, bits 7:3

| | |
|------------------|--|
| Function | Sets the PWM Frequency or SENT Tick Time |
| Syntax | Quantity of bits: 5 |
| Related Commands | outmsg_mode |
| Values | Refer to Table 14: PWM Frequency / SENT Tick Times for values. |
| Options | |
| Examples | |

Table 29: qo_c: Address 0x06 bits 15:0

| | |
|------------------|----------------------------------|
| Function | Fine quiescent output adjustment |
| Syntax | Quantity of bits: 16 signed |
| Related Commands | |
| Values | |
| Options | |
| Examples | See Operating Characteristics |

Table 30: sensm_c: Address 0x03, field 2, bits 14:12

| | | |
|------------------|---|--------------|
| Function | Coarse Sensitivity adjustment, SENS_COARSE. Multiplier applied to the nominal factory Sensitivity, SENS _{INIT} . | |
| Syntax | Quantity of bits: 3 | |
| Related Commands | sens_c | |
| Values | 0 = 1× (default) | 4 = 16× |
| | 1 = 2× | 5 = 32× |
| | 2 = 4× | 6 = Not used |
| | 3 = 8× | 7 = Not used |
| Options | | |
| Examples | See Operating Characteristics | |

Table 31: sens_c: Address 0x03, field 1, bits 10:0

| | |
|------------------|---|
| Function | Fine Sensitivity adjustment, SENS_C. Multiplier applied after the Coarse Sensitivity adjustment. |
| Syntax | Quantity of bits: 11 signed |
| Related Commands | sensm_c |
| Values | <p>The graph illustrates the fine sensitivity adjustment. The vertical axis represents the sensitivity multiplier SENS_C, with a default value of 1. The horizontal axis represents the sens_c register value. Two linear segments are shown: one from sens_c = 0 to 0x400, where sensitivity increases from 1 to SENS_C(max); and another from sens_c = 0x400 to 0x7FF, where sensitivity increases from SENS_C(min) to 1. A dashed horizontal line at SENS_C = 1 connects the default point (0, 1) to the end of the second segment (0x7FF, 1).</p> |
| Options | |
| Examples | See Operating Characteristics |

Table 32: `senstc1_hot_c`: Address 0x04, field 1, bits 10:0
`senstc1_cld_c`: Address 0x04, field 2, bits 22:12

| | |
|------------------|--|
| Function | First order Sensitivity Temperature Compensation, segmented for hot ($25^{\circ}\text{C} < T_A \leq 150^{\circ}\text{C}$) and cold ($-40^{\circ}\text{C} \leq T_A < 25^{\circ}\text{C}$) |
| Syntax | Quantity of bits: 11 signed |
| Related Commands | |
| Values | |
| Options | |
| Examples | |

Table 33: `senstc2_hot_c`: Address 0x04, field 1, bits 9:0
`senstc2_cld_c`: Address 0x04, field 2, bits 21:12

| | |
|------------------|---|
| Function | Second order Sensitivity Temperature Compensation, segmented for hot ($25^{\circ}\text{C} < T_A \leq 150^{\circ}\text{C}$) and cold ($-40^{\circ}\text{C} \leq T_A < 25^{\circ}\text{C}$) |
| Syntax | Quantity of bits: 10 signed |
| Related Commands | |
| Values | |
| Options | |
| Examples | |

PACKAGE OUTLINE DRAWING

For Reference Only – Not for Tooling Use

(Reference DWG-0000409, Rev. 1)
Dimensions in millimeters – NOT TO SCALE
Dimensions exclusive of mold flash, gate burs, and dambar protrusions
Exact case and lead configuration at supplier discretion within limits shown




Figure 32: Package UC, 3-Pin SIP

Revision History

| Number | Date | Description |
|--------|------------------|--|
| – | August 24, 2016 | Initial release |
| 1 | December 2, 2016 | Updated Functional Block Diagram (page 1), Features and Benefits (page 2), Electrical Characteristics (Bandwidth, page 5), Magnetic Characteristics (Input Field Range, Initial Sensitivity, page 7), Programmable Characteristics (Output Sensitivity Trim Range, page 9), Figure 8 (page 15), EEPROM Diagnostics (page 17), Diagnostic Summary table (page 18), Table 8 (SENT Output Trigger Signal, page 19), Memory Address Map (pages 38-42), and Package Outline Drawing (page 47) |
| 2 | July 14, 2020 | Updated Table 7 (p. 18), Table 8 (p. 19), and Table 19 (p. 32), and minor editorial updates |

Copyright 2020, Allegro MicroSystems.

Allegro MicroSystems reserves the right to make, from time to time, such departures from the detail specifications as may be required to permit improvements in the performance, reliability, or manufacturability of its products. Before placing an order, the user is cautioned to verify that the information being relied upon is current.

Allegro's products are not to be used in any devices or systems, including but not limited to life support devices or systems, in which a failure of Allegro's product can reasonably be expected to cause bodily harm.

The information included herein is believed to be accurate and reliable. However, Allegro MicroSystems assumes no responsibility for its use; nor for any infringement of patents or other rights of third parties which may result from its use.

Copies of this document are considered uncontrolled documents.

For the latest version of this document, visit our website:

www.allegromicro.com